

## Specifications

| Item                       | Through-beam                                                                             |                                             | Retro-reflective with M.S.R.            | Diffuse-reflective    |                |
|----------------------------|------------------------------------------------------------------------------------------|---------------------------------------------|-----------------------------------------|-----------------------|----------------|
|                            | E3H2-T4                                                                                  | E3H2-T2                                     | E3H2-R                                  | E3H2-DS30             | E3H2-DS10      |
| Sensing distance           | 4 m (adjustable)                                                                         | 2 m                                         | 2 m (teachable)<br>(when using E39-R1S) | 300 mm (teachable)    | 100 mm (fixed) |
| Differential travel        | 20% max of sensing distance                                                              | 10% max of sensing distance                 |                                         |                       |                |
| Light source (wave length) | Infrared LED (880 nm)                                                                    |                                             | Red LED (660 nm)                        | Infrared LED (880 nm) |                |
| Power supply voltage       | 10 to 30 VDC, 10% ripple                                                                 |                                             |                                         |                       |                |
| Current consumption        | 45 mA max                                                                                |                                             |                                         |                       |                |
| Control output             | Load current: 100 mA max. (residual voltage 2 V max.);<br>E3H2-_C_: NPN<br>E3H2-_B_: PNP |                                             |                                         |                       |                |
|                            | Light-on/dark-on selectable by wire                                                      | E3H2-T2_2_: dark on<br>E3H2-T2_1_: light on | Light-on/dark-on selectable by wire     |                       |                |
| Protective circuits        | Power supply reverse polarity protection, output short circuit protection                |                                             |                                         |                       |                |
| Response time              | Operation or reset: 2.5 ms max                                                           | Operation or reset: 1 ms max.               | Operation or reset: 1.1 ms max          |                       |                |
| Sensitivity adjustment     | Potentiometer adjuster                                                                   | —                                           | Teach-in                                | —                     |                |
| Ambient illumination       | Incandescent lamp: 1500 lx max.; Sunlight: 5000 lx max.                                  |                                             |                                         |                       |                |
| Ambient temperature        | Operating: -25 to +55°C                                                                  | Operating: -25 to +50°C                     | Operating: -25 to +55°C                 |                       |                |
| Degree of protection       | EN 60529: IP67                                                                           |                                             |                                         |                       |                |
| Indicators                 | Emitter: Power supply indicator: yellow<br>Receiver: Operation indicator: yellow         |                                             | Output indicator: yellow                |                       |                |
| Weight pre-wired connector | approx 110 g<br>approx 40 g                                                              | approx 90 g<br>approx 30 g                  | approx 55 g<br>approx 20 g              |                       |                |
| Material case lens         | nickel-plated brass<br>plastic                                                           | stainless steel<br>plastic                  | nickel-plated brass<br>plastic          |                       |                |

## Operation

### Sensitivity adjustment

#### E3H2-T4

The emitter of the E3H2-T4 allows an adjustment of the emitted amount of light by turning the potentiometer. Turn the potentiometer clockwise for increasing the amount of emitted light and counter-clockwise for decreasing the amount of emitted light.

#### E3H2-R2

##### a) standard mode

To teach the retro-reflective model E3H2-R, place the sensor with the lens facing the reflector. Press the teach button for 2-5 seconds. For remote teach connect the white wire (Pin 2) for 2-5 seconds to common (-).

The threshold is now set to 50% of the received light level.

##### b) high sensitivity mode (e.g. for semi-transparent models)

To teach the retro-reflective model E3H2-R in high sensitivity mode, place the sensor with the lens facing the reflector. Press the teach button for >8 seconds. For remote teach connect the white wire (Pin 2) for >8 seconds to common (-).

The threshold is now set just below the received light level.

If the teaching was successful the LED should no longer be flashing and a state change occurs when the light is interrupted.

#### E3H2-DS30

##### a) standard mode

To teach the diffuse-reflective model E3H2-DS30, place the object in front of the sensor at the required sensing distance. Press the teach button for 2-5 seconds. For remote teach connect the white wire (Pin 2) for 2-5 seconds to common (-).

The threshold is now set to 50% of the received light level.

When the object is removed, a state change at the sensor should occur. If this is not the case the high sensitivity mode may be required.

##### b) high sensitivity mode

To teach the diffuse-reflective model E3H2-DS30 in high sensitivity mode, place the object in front of the sensor at the required sensing distance. Press the teach button for >8 seconds. For remote teach connect the white wire (Pin 2) for >8 seconds to common (-).

The threshold is now set just below the received light level.

When the object is removed, a state change at the sensor should occur and the LED should no longer be flashing.

For E3H2-T2 and E3H2-DS10 the sensitivity setting is fixed.

### Operation mode selection

The light-on / dark-on operation mode can be selected by wire (except for E3H2-T2). The white wire (Pin 2) can be connected to plus (+), common (-) or left open (not connected) for the default setting.

#### a) E3H2-T4 Receiver

Default setting (wire left open): DARK-ON

Connected to plus (+): LIGHT-ON

Connected to common (-): DARK-ON

#### b) E3H2-R2

Default setting (wire left open): DARK-ON

Connected to plus (+): LIGHT-ON

Connected to common (-): TEACH<sup>\*1</sup>

#### c) E3H2-DS30

Default setting (wire left open): LIGHT-ON

Connected to plus (+): DARK-ON

Connected to common (-): TEACH<sup>\*1</sup>

#### d) E3H2-DS10

Default setting (wire left open): LIGHT-ON

Connected to plus (+): DARK-ON

Connected to common (-): LIGHT-ON

For E3H2-T2 the operation mode is fixed and models with light-on and dark-on operation are available.

<sup>\*1</sup> In case the remote teach operation is required when the white wire is connected to plus (+), add a 2.2 kΩ resistor between the white wire and (+) to avoid a short circuit.