

## Quadrature Speed and Direction Sensors SNG-Q Series

**32304260**  
Issue B

Datasheet



### DESCRIPTION

Honeywell's SNG-Q Series Quadrature Speed and Direction Sensors are designed to provide both speed and direction information. Speed information is provided from digital square wave outputs; direction is provided using a quadrature output with signals 90° phase shifted from each other. With the quadrature output, target direction is determined by output lead/lag phase shifting.

The SNG-Q Series are designed and manufactured using a platform-based approach that enables cost-competitiveness and mechanical and electrical configurability for customers. The Series are designed for applications where enhanced accuracy is required to detect small target features. This accuracy is enabled by dual differential Hall-effect sensor IC technology. The SNG-Q Series provide a wide operating temperature range, robust electrical noise immunity and industry leading environmental sealing capability. This product includes an O-ring seal for pressure applications, and a fixed mounting flange for simple installation using one fastener.

### FEATURES

- Wide operating temperature range: -40 °C to 150 °C [-40 °F to 302 °F]
- Environmental sealing: Moisture ingress protection rated to IP69K
- Robust electrical noise immunity: Electrical noise radiated immunity (EMC) rated to 100 V/m
- High frequency switching capability: 3 Hz to 20 kHz
- Direction information: From phase-shifted dual output signals
- O-ring seal: Enables environmental sealing to mounting surface
- Supply voltage range: 4.5 V to 26 V

### POTENTIAL APPLICATIONS

#### Industrial

- AC induction motors in material handling, agriculture, and construction machines: May be used to help control power delivered by the ac induction motor
- Hydraulic pump motors in material handling, agriculture, and construction machines: May be used to help control power delivered by the hydraulic pump motor
- Escalators and elevators: May be used to help control speed and position

#### Transportation

- Hybrid electric transmissions in heavy duty trucks, buses, agriculture and construction machines: May be used to help control power regulation of the hybrid system
- Wheel speed detection in material handling, agriculture, and construction machines: May be used to detect the speed and direction of the wheels, which translates to the speed and direction of the machine
- Hybrid engines in heavy duty trucks, buses, agriculture and construction machines: May be used to help control power regulation of the hybrid system

Not recommended for Aerospace or Defense applications.

### PORTFOLIO

The SNG-Q Series joins the 1GT Series, [LCZ Series](#), [ZH10 Series](#), [584XX Series](#), [SNDH-T Series](#), and the [SNDH-H Series](#).

# Quadrature Speed and Direction Sensors, SNG-Q Series

**Table 1. Order Guide**

Catalog Listing	Availability	Description
SNG-QPLA-000	Now	SNG-Q Series, 4-wire quadrature speed and direction sensor, plastic housing, 500 mm [19.7 in] cable with leads, right angle exit, 35 mm [1.38 in] housing length
SNG-QPCA-001	Now	SNG-Q Series, 4-wire quadrature speed and direction sensor, plastic housing, 1,25 m [49.2 in] cable with Deutsch DTM04-4P connector, right angle exit, 35 mm [1.38 in] housing length
SNG-QPRA-000	Now	SNG-Q Series, 4-wire quadrature speed and direction sensor, plastic housing, integral Amp Superseal 1.5 connector, right angle exit, 35 mm [1.38 in] housing length
SNG-QPMB-000	Coming soon	SNG-Q Series, 4-wire quadrature speed and direction sensor, plastic housing, 500 mm [19.7 in] cable with leads, straight exit, 45 mm [1.77 in] housing length





**Figure 1. Nomenclature Guide (All options available now, unless otherwise noted.)**

For example, **SNG-QPLA-000** defines an SNG-Q Series quadrature speed and direction sensor, 500 mm [19.7 in] cable with leads, right angle exit, 35 mm [1.38 in] housing length.

<b>SNG-Q</b> Series	<b>P</b> Housing Material <sup>1</sup>	<b>L</b> Connection Type <sup>2</sup>	<b>A</b> Housing Length	<b>000</b> For Internal Use Only
4-wire quadrature speed and direction sensor	<b>P</b> Plastic	<b>S</b> Integral Amp Superseal 1.5 connector, straight exit <sup>3</sup>	<b>A</b> 35 mm [1.38 in]	
		<b>R</b> Integral Amp Superseal 1.5 connector, right angle exit	<b>B</b> 45 mm [1.77 in] (coming soon)	
		<b>L</b> 500 mm [19.7 in] cable with leads, right angle exit		
		<b>M</b> 500 mm [19.7 in] cable with leads, straight exit (coming soon)		
		<b>C</b> 1,25 m [49.2 in] cable with Deutsch DTM04-MP connector, right angle exit		
		<b>D</b> 1,25 m [49.2 in] cable with Deutsch DTM04-MP connector, straight exit (coming soon) <sup>3</sup>		

<sup>1</sup> Contact Honeywell for other Housing Material options.  
<sup>2</sup> Other cable lengths available upon request.  
<sup>3</sup> Contact Honeywell.

**Table 2. Electrical Specifications**

	Parameter		Comment
	Available Now	Coming Soon	
	 <p>SNG-QPLA-000</p>  <p>SNG-QPCA-001</p>  <p>SNG-QPRA-000</p>	 <p>SNG-QPMB-000</p>	
Supply voltage	4.5 V to 26 V	4.5 V to 26 V	—
Output signal: type	square wave	square wave	Two channel, phase shifted by 90° either channel, may lead or lag. Dependent on target geometry and sensor-to-target orientation; see Figures 2, 3, 4, 5 for recommended orientation.
duty cycle <sup>1</sup>	50% ±10%	50% ±10%	
phase shift	90° ±45°	90° ±45°	
high	≥Vs - 0.5 V	≥Vs - 0.5 V	—
low	≤0.5 V (SNG-QPLA/QPCA), ≤1.75 V (SNG-QPRA)	≤0.5 V	—
load current	40 mA max.	40 mA max.	Each output at all conditions 1 kOhm pull-up resistor, dependent on load resistor. 1 kOhm pull-up resistor, dependent on load resistor. Frequencies >10 kHz may be dependent on target geometry and air gap.
rise time	10 μs max.	10 μs max.	
fall time	5 μs max.	5 μs max.	
frequency	3 Hz to 20 kHz	3 Hz to 20 kHz	
Short circuit protection	50 mA max.	50 mA max.	—
Supply current	12 mA normal, 18 mA max.	12 mA normal, 18 mA max.	all conditions
Reverse voltage	-26 V max.	-26 V max.	10 min duration

<sup>1</sup>Duty cycle = Time high/time total.