# C200H-AD002/DA002 Analog I/O Units

# **Operation Guide**

Revised September 1995





# Notice:

OMRON products are manufactured for use according to proper procedures by a qualified operator and only for the purposes described in this manual.

The following conventions are used to indicate and classify precautions in this manual. Always heed the information provided with them. Failure to heed precautions can result in injury to people or damage to the product.



WARNING Indicates information that, if not heeded, could possibly result in loss of life or serious injury.

Caution Indica

Indicates information that, if not heeded, could result in relatively serious or minor injury, damage to the product, or faulty operation.

# **OMRON Product References**

All OMRON products are capitalized in this manual. The word "Unit" is also capitalized when it refers to an OMRON product, regardless of whether or not it appears in the proper name of the product.

The abbreviation "Ch," which appears in some displays and on some OMRON products, often means "word" and is abbreviated "Wd" in documentation in this sense.

The abbreviation "PC" means Programmable Controller and is not used as an abbreviation for anything else.

# Visual Aids

The following headings appear in the left column of the manual to help you locate different types of information.

- **Note** Indicates information of particular interest for efficient and convenient operation of the product.
- 1, 2, 3... 1. Indicates lists of one sort or another, such as procedures, checklists, etc.

#### © OMRON, 1995

All rights reserved. No part of this publication may be reproduced, stored in a retrieval system, or transmitted, in any form, or by any means, mechanical, electronic, photocopying, recording, or otherwise, without the prior written permission of OMRON.

No patent liability is assumed with respect to the use of the information contained herein. Moreover, because OMRON is constantly striving to improve its high-quality products, the information contained in this manual is subject to change without notice. Every precaution has been taken in the preparation of this manual. Nevertheless, OMRON assumes no responsibility for errors or omissions. Neither is any liability assumed for damages resulting from the use of the information contained in this publication.

# **TABLE OF CONTENTS**

SEC	CTION 1	
Syst	tem Design	1
<b>1</b> -1	Introduction	2
1-2	Safety Precautions	2
1-3	Basic Configuration	3
1-4	Example Configurations	4
1-5	System Considerations	5
SEC	CTION 2	
C20	0H-AD002 Analog Input Unit	7
2-1	Before Operation	8
2-2	Bit and DM Area Allocations	13
2-3	Functions and Programming	18
2-4	Data Setting and Programming Examples	29
2-5	Troubleshooting	31
SEC	CTION 3	
C20	0H-DA002 Analog Output Units	33
3-1	Before Operation	34
3-2	Bit and DM Allocations	39
3-3	Troubleshooting	40
App	pendices	
A S	tandard Models	43
ΒS	pecifications	45
СD	Data Memory Coding Sheet	51
Inde	ΡΧ	55
	· · · · · · · · · · · · · · · · · · ·	
Rev	ision History	57

# About this Manual:

This guide describes the installation and operation of the C200H-AD002 Analog Input Unit and the C200H-DA002 Analog Output Unit and includes the sections described below.

The C200H-AD002 Analog Input Unit and the C200H-DA002 Analog Output Unit are analog-digital and digital-analog converters designed to work with the C200H or C200HS PC.

The C200H-AD002 can convert up to eight analog inputs into digital form. The operator can select from four input ranges: 1 to 5 V, 0 to 10 V, –10 to 10 V, and 4 to 20 mA. Useful functions, such as scaling, mean value, peak value, and square root, are built-in.

The C200H-DA002 can convert four digital signals into analog outputs. The operator can select from two output ranges: –10 to 10 V and 4 to 20 mA.

Please read this manual carefully and be sure you understand the information provided before attempting to install and operate the C200H-AD002 or the C200H-DA002.

Section 1 describes the types of applications in which Analog I/O Units are used.

*Section 2* describes the installation and operation of the C200H-AD002 Analog Input Unit, from installation and wiring through programming and operation.

*Section 3* describes the installation and operation of the C200H-DA002 Analog Output Unit, from installation and wiring through programming and operation.

# **WARNING** Failure to read and understand the information provided in this manual may result in personal injury or death, damage to the product, or product failure. Please read each section in its entirety and be sure you understand the information provided in the section and related sections before attempting any of the procedures or operations given.

# SECTION 1 System Design

This section describes the basic uses of Analog I/O Units in a control system and illustrates the type of applications in which they might be found.

1-1	Introduction	2
1-2	Safety Precautions	2
1-3	Basic Configuration	3
1-4	Example Configurations	4
1-5	System Considerations	5

### **1-1** Introduction

The C200H-AD002 Analog Input Unit is used to convert the output of analog field devices, usually sensors, to a digital form that the PC can read. The C200H-DA002 Analog Output Unit converts the digital output of the PC to analog signals which drive analog field devices.



### 1-2 Safety Precautions

- Be sure to read this manual carefully and understand the explanations before attempting any of the procedures described herein. OMRON accepts no responsibility for any damage or injury that may result from carrying out any operation that is not covered in this manual.
- Be sure to turn off the power supply to the PC before carrying out any of the following operations:
  - a) Mounting or removing a Unit.
  - b) Setting switches.
  - c) Mounting or removing a Terminal Block or connectors.
  - d) Wiring the system or Units.
- Use twisted-pair cables and keep high-voltage lines and power lines in separate ducts to reduce the risk of malfunctions due to electrical noise.
- Before turning on the power supply, check to be sure that the switch settings and wiring are correct.
- Check to be sure that the user program operates correctly.

# **1-3 Basic Configuration**

This diagram shows some of the possible field devices for the Analog I/O Units. Any I/O device can be used as long as voltage/current requirements fall within the specified ranges.

The I/O device connected to the Analog I/O Unit will often serve as an interface for another device. For example, a preamplifier may amplify the output of a pressure gauge to the level required for the Analog Input Unit and a regulator may interface a heating system to control temperature.



# **1-4 Example Configurations**

Below are two examples of how Analog I/O Units can be used in control systems. The first diagram shows a temperature regulating system and the second shows a servomotor positioning system.



# **1-5** System Considerations

Number of UnitsC200HS/C200H Analog I/O Units are classified as Special I/O Units. A maximum total of ten Special I/O Units (including PC Link Units) can be mounted to<br/>the CPU Rack, Expansion I/O Racks, and Slave Racks of a single PC. A single<br/>C200H-NC211 Position Control Unit counts as two Units.

The Units that belong to the various Special I/O Unit groups are shown in the following table. Their usage is limited according to the maximum current provided for the Rack and the amount of current consumed by each Unit. For details, refer to the *C200HS* or *C200H Installation Guide*.

Slave RacksCertain limitations apply to the number of Special I/O Units that can be mounted<br/>on Slave Racks. The following table shows the maximum number of Group A, B,<br/>C, and D Special I/O Units that can be mounted on a single Slave Rack when<br/>only Units of that group are used.

A	В	C	D
High-speed Counters Position Control Units (NC111/112) ASCII Units Analog I/O Units ID Sensor Units Fuzzy Logic Units	High-density I/O Units Temperature Control Units PID Control Units Cam Positioner Units	Temperature Sensor Units Voice Units	Position Control Units (NC211)
4 Units			
	8 Units		
		6 Units	
			2 Units

If Units from any of the four groups are to be combined, then both of the following two equations must be satisfied.

 $3A + B + 2C + 6D \leq 12$  $A + B + C + D \leq 8$ 

Units can be mounted on other Racks as well, until the maximum total of ten Units has been reached. Remember, however, that a single C200H-NC211 Position Control Unit counts as two Units. PC Link Units must also be counted among the total of ten Units.

**System Configuration Considerations** C200HS/C200H Special I/O Units are allocated IR area words according to the unit number switch settings on their front panels. They do not use the words of the slots in which they are mounted. For details regarding data area allocations, refer to 2-2 and 3-2 IR and DM Bit Allocations.

With the C200H, do not mount an Analog I/O Unit in the two slots adjacent to the CPU. Doing so would prevent peripheral devices such as the Programming Console from being connected.

Special I/O Units cannot be used on a C200H Remote I/O Slave Rack if the Slave Rack is connected to different PC (i.e., C500, C1000H, or C2000H).

**Precautions** Be sure to turn off the power supply to the PC before installing or disconnecting Units or connecting lines.

To reduce the risk of malfunctioning due to electrical noise, wire input and output lines in separate ducts from high-voltage and power lines.

For further wiring precautions, refer to the respective sections on wiring for Analog Input Units and Analog Output Units.

# SECTION 2 C200H-AD002 Analog Input Unit

This section provides the information required to install and operate a C200H-AD002 Analog Input Unit.

2-1	Before	efore Operation						
	2-1-1	Nomenclature and Functions	8					
	2-1-2	Switch Settings	9					
	2-1-3	Wiring	9					
2-2	Bit and	DM Area Allocations	13					
2-3	Functio	ns and Programming	18					
	2-3-1	Conversion Prohibit Settings	18					
	2-3-2	Input Signal Range Setting	19					
	2-3-3	Conversion Data Type Setting	20					
	2-3-4	Square Root Function	21					
	2-3-5	Scaling Function	22					
	2-3-6	Mean Value Function	24					
	2-3-7	Peak Value Function	25					
	2-3-8	Limit Warning Function	25					
	2-3-9	Input Disconnection Detection Function	27					
2-4	Data Se	tting and Programming Examples	29					
	2-4-1	Data Settings	29					
	2-4-2	Programming	30					
2-5	Trouble	shooting	31					

# 2-1 Before Operation

### 2-1-1 Nomenclature and Functions



#### Indicators

Indicator	Color	Function
RUN	Green	Lit when the Analog Input Unit is operating correctly. If operation is not normal, this indicator turns OFF and Unit operation is stopped.
BROKEN WIRE	Red	Lit when an input signal wire is disconnected. This indicator operates only when the input range is set to 1 to 5 V/4 to 20 mA.
	1	

#### Functions

The following table briefly outlines the basic functions of the C200H-AD002. These functions are covered in more detail in *2-3 Functions and Programming*.

Function	Explanation
Conversion prohibit setting	Unnecessary conversion processing time can be reduced by disabling analog-to-digital conversion for unused inputs. Disabling conversion can also reduce the sampling period for each input.
Input range setting	The input range can be set for each input number according to the input signal level that is to be used.
Conversion data type setting	Sets whether the converted digital output is BCD or binary.
Square root	Converts quadratic data, such as thermocouple input, to linear data.
Scaling	Converts an analog input signal to a preset range of BCD data for output.
Mean value	Sums the sampling data for the specified number of samples, eliminates the minimum and maximum values, calculates the mean value from the remaining values, and outputs that value.
Peak value	Holds the maximum values for A/D conversion data, scaling data, mean data, and square root data, and outputs them as output data.
Limit warning	The Warning Flag is turned ON if the A/D conversion data, scaling data, mean data, or square root data exceeds the specified upper- or lower-limit values.
Disconnection detection	The Disconnection Detection Flag is turned ON and the BROKEN WIRE indicator is lit if the input signal wire becomes disconnected when 1 to 5 V/4 to 20 mA are set.

### 2-1-2 Switch Settings

**Unit Number Switch** 

The unit number (MACHINE No.) is the only setting necessary on the Analog Input Unit. Always turn off the power before setting the unit number. Use a flatblade screwdriver, being careful not to damage the slot in the screw. Be sure not to leave the switch midway between settings.



Switch setting	Unit number	IR words	DM words
0	Unit #0	IR 100 to 109	DM 1000 to 1043
1	Unit #1	IR 110 to 119	DM 1100 to 1143
2	Unit #2	IR 120 to 129	DM 1200 to 1243
3	Unit #3	IR 130 to 139	DM 1300 to 1343
4	Unit #4	IR 140 to 149	DM 1400 to 1443
5	Unit #5	IR 150 to 159	DM 1500 to 1543
6	Unit #6	IR 160 to 169	DM 1600 to 1643
7	Unit #7	IR 170 to 179	DM 1700 to 1743
8	Unit #8	IR 180 to 189	DM 1800 to 1843
9	Unit #9	IR 190 to 199	DM 1900 to 1943

**Note** 1. The unit number setting switch is factory set to 0.

- 2. If two or more Special I/O Units are assigned the same unit number, an I/O UNIT OVER error will be generated and the PC will not operate.
- 3. Make the unit number settings with the power turned off to the PC. If the settings are made with the power on, they will not go into effect until either the power is turned off and then on again or the Special I/O Unit Restart Flag (AR0100 to AR0109) is turned ON and then OFF again.

### 2-1-3 Wiring

#### Compatible Connector

One MR-34LFG Connector Set is included with each Unit. The set includes an MR-34FG Connector and MR-34L Cover made by Honda Communications.

#### **Pin Allocation**

Pin	Name		Pin	Name	Pin	Name	
no.			no.		no.		
12	Common (–)	Input 7			34	Common (–)	Input 8
11	Current input (+)				33	Current input (+)	
10	Voltage/Current input (+)		22	Analog ground (AG)	32	Voltage/Current input (+)	
9	Common (–)	Input 5	21	Shield	31	Common (–)	Input 6
8	Current input (+)		20	Shield	30	Current input (+)	
7	Voltage/Current input (+)		19	Shield	29	Voltage/Current input (+)	
6	Common (–)	Input 3	18	Shield	28	Common (–)	Input 4
5	Current input (+)		17	Shield	27	Current input (+)	
4	Voltage/Current input (+)		16	Shield	26	Voltage/Current input (+)	
3	Common (–)	Input 1	15	Shield	25	Common (–)	Input 2
2	Current input (+)		14	Shield	24	Current input (+)	
1	Voltage/Current input (+)		13	Frame ground (FG)	23	Voltage/Current input (+)	

- **Note** 1. Short the current input (+) and voltage/current input (+) terminals when using a current input.
  - 2. All of the shield terminals (terminals 14 through 21) are shorted within the Unit. Wire each input's shield wire to any of these terminals.

#### **Input Wiring Diagram**



**Note** In order to prevent effects from noise, connect the shield terminals to the FG terminal, although in some cases it might be better to connect to the AG terminal.

#### **Wiring Methods**

Use the connectors provided with the Unit to wire input lines. (Connector: MR-34FG; Cover: MR-34L; both manufactured by Honda Communications; Connector/Cover Set: MR-34LFG).

Be sure to tighten the lock screws whenever attaching the connector to the Unit.



Do not forget to connect one of cable shield terminals to the FG terminal.

Do not remove the protective seal from the Unit until wiring has been completed. This seal will prevent wire clippings and other debris from entering the Unit and possibly preventing proper operation. Always remove this seal before operation. If the seal is left in place, the Unit may overheat, possibly causing improper operation or damage to the Unit.



#### Input Wiring Considerations

When wiring inputs, apply the following points to avoid noise interference and optimize Analog Input Unit performance.

- Use shielded twisted-pair cable for external connections and power lines.
- Route input cables separately from the AC cable, and do not run the Unit's cables near a main circuit cable, high voltage cable, or a non-PC load cable.
- Be sure to install surge-absorbing diodes or surge absorbers for inductive loads (relays, solenoids, electromagnetic valves, etc.) They should be installed right next to relays and solenoids. Use surge-absorbing diodes with a dielectric strength of at least five times the circuit voltage.



- If there is noise interference from power lines (if, for example, the power supply is shared with electrical welding devices or electrical discharge machines, or if there is a high-frequency generation source nearby) install a noise filter at the power supply input area.
- Use at least a class-3 ground (to 100  $\Omega$  or less), with as heavy a wire as possible (i.e., at least 1.25 mm<sup>2</sup>).

### 2-2 Bit and DM Area Allocations

**IR Area Allocation** 

C200H Analog Input Units are allocated ten words each from the portion of the IR area (IR 100 to IR 199) that is reserved for Special I/O Units. The words that are allocated a particular Analog Input Unit depend on the setting of the unit number on the front panel of the Unit. Those ten words are then reserved as an I/O refresh data area, and the bits that comprise that area are refreshed with every I/O refresh cycle by the PC.



**Note** The unit number that is set for an Analog Input Unit must not be used for any other Special I/O Unit. If the same unit number is set more than once, an I/O UNIT OVER error will be generated and operation will be stopped.

#### **DM Area Allocation**



(For more information regarding DM area allocation, refer to *DM Allocations* at the end of this section.)

#### **IR Allocations**

I/O	Wd		Bit														
	(IR)	15	14	13	12	11	10	09	08	07	06	05	04	03	02	01	00
Out	n		(	)			(	)				Pea	k value	e execu	ition		
										Input 8	Input 7	Input 6	Input 5	Input 4	Input 3	Input 2	Input 1
In	n+1	Sign					Input 1	A/D c	onvers	ion dat	a or pro	ocessir	ng data				
	n+2	Sign					Input 2	A/D c	onvers	ion data	a or pro	ocessir	ng data				
	n+3	Sign					Input 3	A/D c	onvers	ion data	a or pro	ocessir	ng data				
	n+4	Sign					Input 4	A/D c	onvers	ion data	a or pro	ocessir	ng data				
	n+5	Sign					Input 5	A/D c	onvers	ion data	a or pro	ocessir	ng data				
	n+6	Sign Input 6 A/D conversion data or processing data															
	n+7 Sign Input 7 A/D conversion data or processing data																
	n+8	Sign	Input 8 A/D conversion data or processing data														
	n+9		Limit warning Disconnection detecti								ection						
		Input 8	Input 7	Input 6	Input 5	Input 4	Input 3	Input 2	Input 1	Input 8	Input 7	Input 6	Input 5	Input 4	Input 3	Input 2	Input 1

#### **A/D Conversion Data**

Input range	Binary data	BCD data
0 to 10 V, 1 to 5 V, or 4 to 20 mA	0000 to 0FA0	0000 to 4000
–10 to 10 V	87D0 to 8001, 0000 to 07D0 (–07D0 to –0001, 0000 to 07D0)	A000 to 8001, 0000 to 2000 (-2000 to -0001, 0000 to 2000)

**Note** When the input range is set to -10 V to +10 V, the 15<sup>th</sup> bit indicates the sign. A bit status of 0 indicates "+" and a bit status of 1 indicates "-." There is no sign bit when the scaling or square root function is being executed.

**Processing Data** When scaling, mean value processing, peak value, or square root calculation is executed, the resulting data is output.

**Note** When scaling is executed, it is set in IR words n+1 through n+8 in BCD.

#### **IR Area Contents: Outputs**

Address		Item	Contents			
Word (IR)	Bit					
n	15 to 08		Not used. Set these bits to 00 (OFF).			
	07 to 00	Peak Value ON Bits	Turn these bits to 1 (ON) to execute the peak value function for the corresponding input. Bits 00 through 07 correspond to inputs 1 through 8. Refer to <i>2-3-7 Peak Value Function</i> for more details.			

#### **IR Area Contents: Inputs**

Word (IR)	Bit	Item	Contents			
n+1	15 to 00	Input 1 A/D conversion data	The A/D conversion data is set here for each input.			
n+2	15 to 00	Input 2 A/D conversion data or processing data	The conversion data range is as follows when the input signal range is set to 0 to 10 V, 1 to 5 V, or 4 to 20 mA: BCD data: 0000 to 4000			
n+3	15 to 00	Input 3 A/D conversion data or processing data	Binary data: 0000 to 0FA0 The conversion data range is as follows when the input signal range			
n+4	15 to 00	Input 4 A/D conversion data or processing data	is set to -10 to 10 V: BCD data: A000 to 8001, 0000 to 2000			
n+5	15 to 00	Input 5 A/D conversion data or processing data	<ul> <li>Binary data: 87D0 to 8001, 0000 to 07D0</li> <li>When the input range is set to -10 V to +10 V, the 15<sup>th</sup> bit indicates the sign. A bit status of 0 indicates "+" and a bit status of 1 indicates "" (There is no sign bit when the scaling or square root function is being executed.)</li> <li>The processing results for the scaling, mean value, peak value, and square root functions are output here when those functions are being executed.</li> </ul>			
n+6	15 to 00	Input 6 A/D conversion data or processing data				
n+7	15 to 00	Input 7 A/D conversion data or processing data				
n+8	15 to 00	Input 8 A/D conversion data or processing data				
n+9	15 to 08	Limit warning	When the limit warning has been set, these bits are turned ON to indicate that the corresponding input's value has exceeded the range. Bits 08 through 15 correspond to inputs 1 through 8.			
	07 to 00	Disconnection detection	These bits are turned ON to indicate that a disconnection or broken wire has occurred in the corresponding input. Bits 00 through 07 correspond to inputs 1 through 8.			

#### **DM Allocations**

DM								В	it							
word	15	14	13	12	11	10	09	08	07	06	05	04	03	02	01	00
m			0		0	0	Limit	Data	Conversion prohibit setting							
							mode	setting	Input 8	Input 7	Input 6	Input 5	Input 4	Input 3	Input 2	Input 1
m+1	Input signal range (00 specifies -10 to +10 V, 01 spe							01 spec	cifies 0	to 10 \	/, and 1	0 spec	ifies 1	to 5 V/4	1 to 20	mA.)
	Inp	ut 8	Inp	ut 7	Inp	Input 6 Input 5			Input 4 Input 3			ut 3	Input 2 Input 1			ut 1
m+2			S	caling e	execution	on					Mea	an value	e execi	ution		
	Input 8	Input 7	Input 6	Input 5	Input 4	Input 3	Input 2	Input 1	Input 8	Input 7	Input 6	Input 5	Input 4	Input 3	Input 2	Input 1
m+3			Squ	are roo	t execu	ution					Limit	warnir	ng exec	ution		
	Input 8	Input 7	Input 6	Input 5	Input 4	Input 3	Input 2	Input 1	Input 8	Input 7	Input 6	Input 5	Input 4	Input 3	Input 2	Input 1
m+4						In	put 1 so	caling:	lower-li	mit val	ue					
m+5		Input 1 scaling: upper-limit value														
m+6		Input 2 scaling: lower-limit value														
m+7		Input 2 scaling: upper-limit value														
m+8						In	put 3 so	caling:	lower-li	mit val	ue					
m+9						In	put 3 so	caling:	upper-li	imit val	ue					
m+10						In	put 4 so	caling:	lower-li	mit val	ue					
m+11						In	put 4 so	caling:	upper-li	imit val	ue					
m+12						In	put 5 so	caling:	lower-li	mit val	ue					
m+13						In	put 5 so	caling:	upper-li	imit val	ue					
m+14						In	put 6 so	caling:	lower-li	mit val	ue					
m+15						In	put 6 so	caling:	upper-li	imit val	ue					
m+16						In	put 7 so	caling:	lower-li	mit val	ue					
m+17						In	put 7 so	caling:	upper-li	imit val	ue					
m+18						In	put 8 so	caling:	lower-li	mit val	ue					
m+19						In	put 8 so	caling:	upper-li	imit val	ue					
m+20					Input	t 1 mea	an value	proce	ssing: r	number	of san	nples				

DM								В	it							
word	15	14	13	12	11	10	09	08	07	06	05	04	03	02	01	00
m+21		Input 2 mean value processing: number of samples														
m+22					Input	3 mea	an value	proce	ssing: r	number	of san	nples				
m+23					Input	4 mea	an value	proce	ssing: r	number	of san	nples				
m+24					Input	5 mea	an value	proce	ssing: r	number	of san	nples				
m+25					Input	6 mea	an value	e proce	ssing: r	number	of san	nples				
m+26					Input	7 mea	an value	e proce	ssing: r	number	of san	nples				
m+27					Input	8 mea	an value	proce	ssing: r	number	of san	nples				
m+28						Inpu	t 1 limit	warnin	g: lowe	er-limit v	value					
m+29						Input	t 1 limit	warnin	g: uppe	er-limit	value					
m+30						Inpu	t 2 limit	warnin	g: lowe	er-limit v	value					
m+31						Input	t 2 limit	warnin	g: uppe	er-limit	value					
m+32						Inpu	t 3 limit	warnin	g: lowe	er-limit v	value					
m+33						Input	t 3 limit	warnin	g: uppe	er-limit	value					
m+34						Inpu	t 4 limit	warnin	g: lowe	er-limit v	value					
m+35						Input	t 4 limit	warnin	g: uppe	er-limit	value					
m+36						Inpu	t 5 limit	warnin	g: lowe	er-limit v	value					
m+37						Input	t 5 limit	warnin	g: uppe	er-limit	value					
m+38						Inpu	t 6 limit	warnin	g: lowe	er-limit v	value					
m+39						Input	t 6 limit	warnin	g: uppe	er-limit	value					
m+40						Inpu	t 7 limit	warnin	g: lowe	er-limit v	value					
m+41						Input	t 7 limit	warnin	g: uppe	er-limit	value					
m+42						Inpu	t 8 limit	warnin	g: lowe	er-limit v	value					
m+43						Input	t 8 limit	warnin	g: uppe	er-limit	value					

#### **DM Contents**

DM word(s)	Bits	Item	Data contents				
m	15 to 10		Not used.				
	09	Limit warning mode	Sets the operating mode for the limit warning function. This setting applies to all 8 inputs.				
			0: Mode 1 (normal warning) 1: Mode 2 (sequence warning)				
			Refer to 2-3-8 Limit Warning Function for more details.				
	08	Conversion data type	Sets the data type of the conversion data to binary or BCD. This setting applies to all 8 inputs.				
			0: Binary 1: BCD				
	07 to 00	Conversion prohibit setting	Turn these bits turned ON to disable A/D conversion for the corresponding input. Bits 00 through 07 correspond to inputs 1 through 8.				
			0: Conversion enabled 1: Conversion disabled				
m+1	15 and 14	Input signal range for input 8	Each pair of bits sets the input signal range for the				
	13 and 12	Input signal range for input 7	corresponding input, as follows.				
	11 and 10	Input signal range for input 6	(110  m m s) is the higher bit.)				
	09 and 08	Input signal range for input 5	01: 0 to 10 V				
	07 and 06	Input signal range for input 4	10: 1 to 5 V/4 to 20 mA				
	05 and 04	Input signal range for input 3	11: Not used.				
	03 and 02	Input signal range for input 2					
	01 and 00	Input signal range for input 1					

DM word(s)	Bits	ltem	Data contents
m+2	15 to 08	Scaling execution	Turn these bits turned ON to execute the scaling function for the corresponding input. Bits 08 through 15 correspond to inputs 1 through 8.
			<ul><li>0: Scaling function won't be executed.</li><li>1: Scaling function will be executed.</li></ul>
			Refer to 2-3-5 Scaling Function for more details.
	07 to 00	Mean value execution	Turn these bits turned ON to execute the mean value function for the corresponding input. Bits 00 through 07 correspond to inputs 1 through 8.
			<ul><li>0: Mean value function won't be executed.</li><li>1: Mean value function will be executed.</li></ul>
			Refer to 2-3-6 Mean Value Function for more details.
m+3	15 to 08	Square root execution	Turn these bits turned ON to execute the square root function for the corresponding input. Bits 08 through 15 correspond to inputs 1 through 8.
			<ul><li>0: Square root function won't be executed.</li><li>1: Square root function will be executed.</li></ul>
			Refer to 2-3-4 Square Root Function for more details.
	07 to 00	Limit warning execution	Turn these bits turned ON to execute the limit warning function for the corresponding input. Bits 00 through 07 correspond to inputs 1 through 8.
			<ul><li>0: Limit warning function won't be executed.</li><li>1: Limit warning function will be executed.</li></ul>
			Refer to 2-3-8 Limit Warning Function for more details.
m+4 to m+19	15 to 00	Scaling data	The scaling data (upper and lower limits) is set in BCD (0000 to 9999), using two words for each input. Set the lower limit in the first of the two words and the upper limit in the second, and make sure that the lower limit is smaller than the upper limit.
			Refer to 2-3-5 Scaling Function for more details.
m+20 to m+27	15 to 00	Number of terms for calculating mean value	The number of samples to be taken for calculating the mean value is set in BCD (0003 to 9999) for each input. DM words m+20 through m+27 correspond to inputs 1 through 8.
			Refer to 2-3-6 Mean Value Function for more details.
m+28 to m+43	15 to 00	Limit warning data	The limit warning data (upper and lower limits) is set in BCD using two words for each input. Set the lower limit in the first of the two words and the upper limit in the second, and make sure that the lower limit is smaller than the upper limit.
			The setting range is 0000 to 4000. (The scaling data's upper and lower limits are used when the scaling function is being executed.)
			Refer to 2-3-8 Limit Warning Function for more details.

### **2-3** Functions and Programming

The C200H-AD002 Analog Input Unit provides nine functions:

- *1, 2, 3...* 1. Conversion prohibit settings
  - 2. Input signal range settings
  - 3. Conversion data type setting
  - 4. Square root function
  - 5. Scaling function
  - 6. Mean value processing function
  - 7. Peak value function
  - 8. Limit warning function
  - 9. Disconnection detection function
    - (This function can be used with the 1 to 5 V/4 to 20 mA input range only.)

These functions are set using Unit switches and Peripheral Devices, such as a Programming Console. The words allocated to the Unit in the DM Area (DM m to DM m+43) cannot be written from user program and all data set in these words must be written from a Peripheral Device.

When inputting data from a Programming Console, use the operations to change present values. When inputting from the SSS (SYSMAC Support Software), use the DM editing operations.

The data set in the DM area is transferred to the Analog Input Unit when either of the following steps is taken. Be sure to perform one or the other of these steps whenever new data has been set or data has been changed.

- Turning ON  $\rightarrow$  OFF  $\rightarrow$  ON the power to the C200H/C200HS CPU.
- Turning OFF  $\rightarrow$  ON the Restart Bit allocated to the Unit as a Special I/O Unit (AR 0100 to 0109).

The above functions 3 to 8 can be used at the same time. Data will be processed in the following sequence and the final results will be output to words n+1 to n+8: analog-to-digital conversion  $\rightarrow$  square root  $\rightarrow$  scaling  $\rightarrow$  mean value  $\rightarrow$  peak value.

### 2-3-1 Conversion Prohibit Settings

Function The A/D conversion processing period for the used inputs can be reduced by stopping conversion for unused inputs. The data is fixed at 0000 for inputs with the conversion prohibit setting. Setting Method The conversion prohibit setting is made in bits 00 to 07 of DM word m. Set the corresponding bit to "1" to prohibit conversion for that input. Bit 07 06 05 04 03 02 01 00 DM m 0: Conversion enabled 1: Conversion disabled nput 6 nput 5 Input 3 nput 2 nput 8 Input 4 nput 7 nput ' Sampling Period The "sampling period" is the amount of time between A/D conversion processing for a given input. The sampling period for this Unit can be determined from the following equation: Sampling period = 4 ms + (number of enabled inputs)  $\times$  2.5 ms

The base sampling period of 4 ms excludes effects such as temperature drift. This processing is performed every time after A/D conversion has been performed for the last enabled input.

Number of enabled inputs	Sampling period
1	6.5 ms
2	9.0 ms
3	11.5 ms
4	14.0 ms
5	16.5 ms
6	19.0 ms
7	21.5 ms
8	24.0 ms

Stopping conversion for unused inputs reduces the number of enabled inputs and the sampling period, as shown in the following table.

Additional InformationThe following amount of time is required to read the conversion data to the CPU.Min. time required = (sampling period) + (cycle time)

Max. time required = (sampling period) + (cycle time)  $\times$  2

### 2-3-2 Input Signal Range Setting

**Function** Sets the input signal range to match the input signal being used for each input.

Setting Method

The input signal range setting for each input is made with two bits in DM word m+1. Set the corresponding pair of bits to the desired value for that input.



	В	it	Input signal range				
	Leftmost bit	Rightmost bit					
0		0	–10 to +10 V				
0		1	0 to +10 V				
1		0	+1 to +5 V/+4 to +20 mA				
1		1	Not used.				

#### Example

This example shows how to set DM word m+1 to set the following input signal ranges.

Inputs	Input signal range	Bit settings
Inputs 1 to 4	+1 to +5 V	10
Inputs 5 and 6	–10 to +10 V	00
Inputs 7 and 8	0 to +10 V	01



Set DM word m+1 to "50AA" to set the desired input signal ranges.

#### Section 2-3

### 2-3-3 Conversion Data Type Setting

Function

Sets whether the digital conversion data is output in binary or BCD. The digital data is output to IR words n+1 through n+8.

The scaling and square root functions can process BCD data only, so the data type setting is ignored when these functions are being used.

Setting Method Set the data type with bit 8 of DM word m.



#### A/D Conversion Data

The following table shows the range of data that is output to IR words n+1 through n+8.

Input range	Binary data	BCD data
0 to +10 V, +1 to +5 V, +4 to +20 mA	0000 to 0FA0	0000 to 4000
-10 to +10 V	87D0 to 8001, 0000 to 07D0 (-07D0 to -0001, 0000 to 07D0)	A000 to 8001, 0000 to 2000 (-2000 to -0001, 0000 to 2000)

**Note** When the input range is set to -10 V to +10 V, the 15<sup>th</sup> bit indicates the sign. A bit status of 0 indicates "+" and a bit status of 1 indicates "-." There is no sign bit when the scaling or square root function is being executed.

#### **Binary Data Conversion**



#### **BCD Data Conversion**



- Note 1. The maximum digital output value will be used if the analog input signal exceeds the maximum value of the specified input signal range (+10 V or +5 V/+20 mA) and the minimum digital output value will be used if the analog input signal falls below the minimum value of the specified input signal range (0 V, +1 V/+4 mA, or -10 V).
  - 2. The digital output value will be 0000 when the input signal range is set to -10 to +10 V and the analog input signal is 0 V. The sign bit will be 0, and there is no output value of 8000.

### 2-3-4 Square Root Function

Function

Converts quadratic input data, such as data from a thermocouple input, to linear data (0000 to 4000 BCD) and outputs the converted data.

This function can be used at the same time as other functions. When the square root function is used together with the scaling or mean value functions, the scaling or mean value processing is performed after the square root processing.

This function operates on BCD data only, so the conversion data type setting is ignored.

**Setting Method** The square root function is set with bits 08 to 15 of DM word m+3. Set the corresponding bit to "1" to enable the square root function for that input.

Bi DM (m + 3)	t 15	14	13	12	11	10	09	08	0: Square root function disabled
	nput 8	- nput 7	nput 6	nput 5	nput 4	nput 3	nput 2	nput 1	function enabled

Square Root Calculation

The square root function is performed with the following equation and the decimal portion of the result is truncated.

Square root data =  $\sqrt{4000}$  × input data (BCD conversion data)

When the input signal range is set to -10 to +10 V, calculate the input data (BCD conversion data) with -10 V as 0000 and +10 V as 4000.

### 2-3-5 Scaling Function

The scaling function converts the digital output values to the scale defined by the specified lower-limit and upper-limit values, then outputs the scaled data. The lower-limit value is the digital output value corresponding to the minimum input value. The upper-limit value is the digital output value corresponding to the maximum input value.

Scaled data for each input is output in IR words n+1 through n+8.

This function operates on BCD data only, so the conversion data type setting is ignored. Except for the BCD limitation, the scaling function can be used with other functions.

Setting Method Two settings must be made to use the scaling function. First, the scaling function must be enabled for the desired input(s), and then the upper- and lower-limit data must be set for those inputs.

*1, 2, 3...* 1. The scaling function is set with bits 08 to 15 of DM word m+2. Set the corresponding bit to "1" to enable the scaling function for that input.



 Set the upper and lower limits for each input in the corresponding pair of words in DM m+4 through DM m+19. The data must be BCD from 0000 to 9999 and the upper-limit value must be greater than the lower-limit value.

DM word	Data
m+4	Input 1 scaling: lower-limit value
m+5	Input 1 scaling: upper-limit value
m+6	Input 2 scaling: lower-limit value
m+7	Input 2 scaling: upper-limit value
m+8	Input 3 scaling: lower-limit value
m+9	Input 3 scaling: upper-limit value
m+10	Input 4 scaling: lower-limit value
m+11	Input 4 scaling: upper-limit value
m+12	Input 5 scaling: lower-limit value
m+13	Input 5 scaling: upper-limit value
m+14	Input 6 scaling: lower-limit value
m+15	Input 6 scaling: upper-limit value
m+16	Input 7 scaling: lower-limit value
m+17	Input 7 scaling: upper-limit value
m+18	Input 8 scaling: lower-limit value
m+19	Input 8 scaling: upper-limit value

#### Scaling Calculation

The scaling calculation is made with the following equation using the preset upper and lower-limit values for the input. The decimal portion of the result is truncated.

Scaled data = input data (BCD conversion data)  $\times \frac{\text{upper limit} - \text{lower limit}}{4000} + \text{lower limit}$ 

When the input signal range is set to -10 to +10 V, calculate the input data (BCD conversion data) with -10 V as 0000 and +10 V as 4000.

- **Note** 1. The resolution is fixed at 1/4000 if the (upper limit lower limit) term is greater than 4000.
  - 2. The resolution will be lower if the (upper limit lower limit) term is less than 4000. For example, the resolution will be 1/2000 if the upper limit lower limit = 2000.
  - 3. The scaling calculation won't be performed if the DM words don't contain BCD data or the upper-limit data ≦ lower-limit data.
  - 4. When the scaling function is executed, the conversion data type setting is ignored and the scaled data is output.

Input signal range: 0 to +10 V Lower limit: 1000 Upper limit: 9000



Example 1

Example 2

Input signal range: -10 to +10 V Lower limit: 1000 Upper limit: 7000



For example, the scaled data for -2 V is calculated as follows:

BCD conversion value for 
$$-2 V = \frac{(-2) - (-10)}{10 - (-10)} \times 4000 = \frac{8}{20} \times 4000 = 1600$$

-2 V scaled data =  $1600 \times \frac{7000 - 1000}{4000} + 1000 = 3400$ 

#### 2-3-6 Mean Value Function

Function

The mean value function collects the specified number of data samples, discards the minimum and maximum values, calculates the mean value of the remaining samples and outputs the result.

The result for each input is output to its corresponding word in IR words n+1 through n+8.

The mean value function can be used in combination with other functions.

Setting Method Two settings must be made to use the mean value function. First, the mean value function must be enabled for the desired input(s), and then the number of samples data must be set for those inputs.

*1, 2, 3...* 1. The mean value function is set with bits 00 to 07 of DM word m+2. Set the corresponding bit to "1" to enable the mean value function for that input.

E DM (m + 2	Bit	07	06	05	04	03	02	01	00	0: Mean value function disabled
	L	Input 8	Input 7	Input 6	Input 5	Input 4	Input 3	Input 2	Input 1	function enabled

2. Set the number of samples for each input in the corresponding word in DM m+20 through DM m+27. The data must be BCD from 0003 to 9999.

DM word	Data
m+20	Input 1 mean value processing: number of samples
m+21	Input 2 mean value processing: number of samples
m+22	Input 3 mean value processing: number of samples
m+23	Input 4 mean value processing: number of samples
m+24	Input 5 mean value processing: number of samples
m+25	Input 6 mean value processing: number of samples
m+26	Input 7 mean value processing: number of samples
m+27	Input 8 mean value processing: number of samples

Mean Value Calculation and Sampling Period

The mean value is calculated using the equation below. The decimal portion of the result is truncated.

Mean value =  $\frac{\text{sum of the samples (except the min. and max. values)}}{\text{number of samples } - 2}$ 

The sampling period between mean value calculations can be determined from the following equation:

Sampling period = (no. of samples)  $\times$  (sampling period per point)

= (no. of samples)  $\times$  (4 ms + (no. of enabled inputs)  $\times$  2.5 ms)

- **Note** 1. The previous mean value result will be output while the mean value processing is being performed (including sample collection).
  - 2. After power is turned on, a value of 0000 will be output until the first mean value calculation is completed.
  - 3. The mean value calculation won't be performed if the data in DM words m+20 through m+27 isn't BCD data from 0003 to 9999.

#### Section 2-3

### 2-3-7 Peak Value Function

The peak value function holds the maximum output value for every input. This function can be used in combination with the scaling, mean value, and square root functions. These functions are performed in the following order:

A/D conversion  $\rightarrow$  square root  $\rightarrow$  scaling  $\rightarrow$  mean value  $\rightarrow$  peak value

The maximum value of the final result will be output to the corresponding word from IR n+1 through IR n+8.

The peak value function can be used in combination with other functions.

Setting Method The peak value function is set with bits 00 to 07 of IR (n). Set the corresponding bit to "1" to enable the peak value function for that input.



0: Peak value function disabled 1: Peak value function enabled

The peak value function will be executed for an input as long as its corresponding control bit is ON. The bits in IR (n) are output bits, so their status can be controlled from the program.

Mean and Peak Values Data will be output as illustrated below when both the mean value and the peak value functions are used. In this example, mean value #2 will be output as the first peak value even if mean value #1 is larger because the Peak Value ON Bit was turned ON after mean value #1 was output.



### 2-3-8 Limit Warning Function

Function	The limit warning function turns on a warning flag in IR $n+9$ when the output data for the corresponding input is outside of the preset range. Bits 08 through 15 of IR $n+9$ are the warning flags for inputs 1 through 8.
Setting Method	Three settings must be made to use the limit warning function. First, the limit warning mode must be set, then the limit warning function must be enabled for the desired input(s), and finally the upper- and lower-limit data must be set for those inputs.

*1, 2, 3...* 1. The limit warning mode is set with bit 09 of DM word m. This mode setting applies to all 8 inputs.



#### Mode 1

The output values are compared to the upper/lower limits from startup.



#### Mode 2

The output values are compared to the upper/lower limits after the output value enters the range between the lower and upper limits.



2. The limit warning function is enabled with bits 00 to 07 of DM word m+3. Set the corresponding bit to "1" to enable the limit warning function for that input.



3. Set the upper and lower limits for each input in the corresponding pair of words in DM m+28 through DM m+43. The data must be BCD from 0000 to 4000 and the upper-limit value must be greater than the lower-limit value. The scaling function's upper/lower limits are used when the scaling function is being executed.

DM word	Data	
m+28	Input 1 lower-limit warning data	
m+29	Input 1 upper-limit warning data	
m+30	Input 2 lower-limit value	
m+31	Input 2 upper-limit value	
m+32	Input 3 lower-limit value	

DM word	Data
m+33	Input 3 upper-limit value
m+34	Input 4 lower-limit value
m+35	Input 4 upper-limit value
m+36	Input 5 lower-limit value
m+37	Input 5 upper-limit value
m+38	Input 6 lower-limit value
m+39	Input 6 upper-limit value
m+40	Input 7 lower-limit value
m+41	Input 7 upper-limit value
m+42	Input 8 lower-limit value
m+43	Input 8 upper-limit value

If the conversion data type setting (bit 08 of DM m) is binary, the output value will be converted to BCD for comparison.

When the input signal range is set to -10 to +10 V, calculate the input data with -10 V as 0000 and +10 V as 4000. (When the scaling function is being used, -10 V=lower-limit value and +10 V=upper-limit value.)

Limit Warning Flags The corresponding Limit Warning Flag (bits 08 to 15 in IR n+9) will be turned ON if the output data in IR words n+1 through n+8 isn't within the range specified with the upper-/lower-limit values. The Limit Warning Flags don't indicate whether the upper or lower limit has been crossed.



- **Note** 1. The Limit Warning Flag won't be turned ON if the output data is outside of the specified range for less than one PC cycle.
  - 2. The limit warning function won't operate if the upper-/lower-limit values are outside of the acceptable setting range (0000 to 4000) or the lower-limit value is greater than the upper-limit value.

### 2-3-9 Input Disconnection Detection Function

Function

The Input Disconnect Flag (bits 00 through 07 of IR n+9) will be turned ON when the input signal level is less than 1 V/4 mA and the input signal range is set at 1 to 5 V/4 to 20 mA. The BROKEN WIRE indicator on the front of the Unit will light when one or more of the Input Disconnect Flags is ON.

**Input Disconnect Flags** 

The Input Disconnect Flags are contained in in word IR n+9, as shown below.



#### Mean Value Processing and Disconnection Detection

I The following diagram shows how a disconnection detection affects the results (output data) produced by the mean value function.



5. The disconnection detection function is valid only when the input signal range is set at 1 to 5 V/4 to 20 mA.

# 2-4 Data Setting and Programming Examples

### 2-4-1 Data Settings

The following settings are used in this example.

#### **Basic Settings**

ltem	Setting
Unit number	0 (allocated words: IR 100 to IR 109 and DM 1000 to DM 1043)
Inputs used	Inputs 1 to 5 (The conversion prohibit bits for inputs 6 to 8 are turned ON.)
A/D conversion data	BCD

#### **Detailed Settings**

Item		Input 5	Input 4	Input 3	Input 2	Input 1
Input signal range		–10 to +10 V	0 to +10 V	4 to 20 mA	1 to 5 V	1 to 5 V
Scaling function	Lower limit			0400	1000	1000
	Upper limit			1000	5000	5000
Number of terms for mean value calculation				50		
Square root function						Yes
Limit warning	Mode				2	
function	Lower limit				1200	
	Upper limit				4800	

#### **DM Area Settings**

Data in the DM area is set using a computer running SSS, a Programming Console, or other Peripheral Device.

After setting the data, turn the PC ON  $\rightarrow$  OFF $\rightarrow$  ON or turn AR 0100 (the Special I/O Unit Restart Bit) OFF $\rightarrow$  ON  $\rightarrow$  OFF to initialize the Unit with the new settings.

DM word	Contents	Data
DM 1000	03E0	Limit warning mode (bit 09 = "1"), BCD (bit 08 = "1"), conversion prohibit (bits 05 to 07 = "1")
DM 1001	006A	Input signal range setting (00 00 00 00 01 10 10 10)
DM 1002	0704	Scaling function (bits 08 to 10 = "1"), mean value function (bit 02 = "1")
DM 1003	0102	Square root function (bit 08 = "1"), limit warning function (bit 01 = "1")
DM 1004	1000	Input 1 lower limit for scaling
DM 1005	5000	Input 1 upper limit for scaling
DM 1006	1000	Input 2 lower limit for scaling
DM 1007	5000	Input 2 upper limit for scaling
DM 1008	0400	Input 3 lower limit for scaling
DM 1009	1000	Input 3 upper limit for scaling
DM 1022	0050	Input 3 number of terms for mean value
DM 1030	1200	Input 2 limit warning function: lower limit
DM 1031	4800	Input 2 limit warning function: upper limit

### 2-4-2 Programming

#### **Reading Output Data**

The converted data (or the results of calculations performed on it) can be read from the output words IR n+1 to IR n+8 and moved to other words in memory using MOV(21) and/or XFER(70). MOV(21) is used to move one word at a time and XFER(70) is used to move more than one word at a time.



#### Reading Output Data (-10 to +10 V Input Range)

The sign bit will be set to "1" when the input setting range is set to -10 to 10 V and the input signal is negative. To separate the sign bit and the actual voltage, use a program that masks the sign bit, as in the following example.

In this example, the A/D Unit's output data is displayed on a display device through the High-density Output Unit with unit number 2.

CN1 (IR 120): Actual data

CN2 (IR 121): Signed data (Bit IR 12100 indicates the sign.)



#### **Peak Value Setting**

The following example shows how to set the peak value function for input 4.



# 2-5 Troubleshooting

#### **Error Detection**

When an error occurs in an input or in the Unit itself, the error is indicated by an output to a flag in the IR, SR, or AR area. The following tables show the various errors that may occur, along with their probable causes and remedies.

Unit error	Probable causes and operations	Possible remedies
Disconnection error	<ul> <li>Causes of error</li> <li>Input signal range is set to "1 to 5V/4 to 20 mA" but the input is less than 1 V/4 mA.</li> </ul>	Check the input signal wires and connector wiring for broken wires or disconnections.
	Disconnect indications	Check the input voltage and current.
	<ul> <li>BROKEN WIRE indicator is lit.</li> </ul>	Turn ON the corresponding conversion
	• The Input Disconnect Flag (IR n+9, bits 00 to 07) that corresponds to the input signal is turned ON. (Bits 00 to 07 correspond to inputs 1 to 8.)	any unused inputs. (Bits 00 to 07 correspond to inputs 1 to 8.)
Limit warning	Causes of error	Check the input signal value.
	<ul> <li>The output data (conversion data or calculation result) isn't within the preset limits.</li> </ul>	Check whether the upper- and lower-limit values are appropriate.
	<ul> <li>Limit warning indications</li> </ul>	
	<ul> <li>The Limit Warning Flag (IR n+9, bits 08 to 15) that corresponds to the input signal is turned ON. (Bits 08 to 15 correspond to inputs 1 to 8.)</li> </ul>	
RUN indicator not lit	The RUN indicator on the Unit is not lit even though power is turned on to the PC, and none of the errors described in this table have occurred.	Replace the Unit.

CPU error	Probable causes and operations	Possible remedies	
CPU waiting	The Special I/O Unit is defective.	• Replace the defective Special I/O Unit.	
	<ul> <li>The PC hasn't begun to run.</li> </ul>	• The defective Unit should appear as \$ signs only in the I/O table read operation.	
I/O Unit Over error	One unit number has been assigned to more than one Special I/O Unit.     Do not assign the same number than one Unit. Use the I/O table than one Unit.		
	<ul> <li>SR 25415 will be turned ON and the PC won't oper- ate when an "I/O Unit Over error" occurs.</li> <li>Flags AR 0000 to AR 0011 indicate the duplicated unit number.</li> </ul>	operation to display unit numbers.	
Special I/O Unit error	• An error has occurred in I/O refreshing between the CPU and the Special I/O Unit.	Check AR 0000 to AR 00015 for the unit number of the Unit in error. After	
	<ul> <li>SR 25415 will be turned ON but PC operation will continue when a "Special I/O Unit error" occurs.</li> </ul>	correcting the error, restart the Unit by toggling the corresponding restart bit (OFF $\rightarrow$ ON $\rightarrow$ OFF) in AR 0100 to AR 0109. If the error recurs after restarting the Unit, replace the Unit.	

#### Special I/O Unit Error Detection Bit (SR)

Bit	Error	Explanation	Operation status
SR 25415	Duplicated unit number	The same number is assigned to more than one Special I/O Unit.	PC operation stops.
	Special I/O Unit error	An error has occurred in the refresh signal between the CPU and the Special I/O Unit	Operation stops only for the faulty Unit.

#### Special I/O Unit Error Flags (AR)

Bit	Item	Function
AR 0000	Unit #0 Error Flag	When one of the CPU errors described above
AR 0001	Unit #1 Error Flag	occurs, the AR bit turns ON for the Unit where the
AR 0002	Unit #2 Error Flag	
AR 0003	Unit #3 Error Flag	
AR 0004	Unit #4 Error Flag	
AR 0005	Unit #5 Error Flag	
AR 0006	Unit #6 Error Flag	
AR 0007	Unit #7 Error Flag	
AR 0008	Unit #8 Error Flag	
AR 0009	Unit #9 Error Flag	

#### Special I/O Unit Restart Bits (AR)

Turn OFF  $\rightarrow$  ON  $\rightarrow$  OFF the Special I/O Unit Restart Bits in the following circumstances:

- After DM data has been set or replaced.
  - To restart Unit operation after clearing an error.

The same effect can be achieved by turning off the power to the PC and then turning it on again.

Bit	ltem	Function
AR 0100	Unit #0 Restart Bit	Special I/O Units can be restarted by turning the
AR 0101	Unit #1 Restart Bit	corresponding bits OFF $\rightarrow$ ON $\rightarrow$ OFF.
AR 0102	Unit #2 Restart Bit	
AR 0103	Unit #3 Restart Bit	
AR 0104	Unit #4 Restart Bit	
AR 0105	Unit #5 Restart Bit	
AR 0106	Unit #6 Restart Bit	
AR 0107	Unit #7 Restart Bit	
AR 0108	Unit #8 Restart Bit	
AR 0109	Unit #9 Restart Bit	

# SECTION 3 C200H-DA002 Analog Output Units

This section provides the information required to install and operate a C200H-DA002 Analog Output Unit.

3-1	Before (	Dperation	34
	3-1-1	Nomenclature and Functions	34
	3-1-2	Switch Settings	35
	3-1-3	Wiring	36
3-2	Bit and	DM Allocations	39
	3-2-1	Programming	40
3-3	Troubles	shooting	40

# 3-1 Before Operation

### **3-1-1 Nomenclature and Functions**



#### Indicators

Indicator	Color	Function
RUN	Green	Lit when the Analog Input Unit is operating correctly. If operation is not normal, this indicator turns OFF and Unit operation is stopped.

#### **Block Diagram**

The following diagram shows the basic internal configuration of the Analog Output Unit.



### 3-1-2 Switch Settings

**Unit Number** 



The switch notch points to the unit number. The switch in the figure to the left is set to 0. Odd numbers, in parentheses here, are not shown on the Unit.

Use a standard screwdriver to set a different unit number for each Analog I/O Unit. IR area memory is allocated according to unit number, as shown in the table below.

Switch number	Unit number	IR words
0	Unit #0	IR 100 to 109
1	Unit #1	IR 110 to 119
2	Unit #2	IR 120 to 129
3	Unit #3	IR 130 to 139
4	Unit #4	IR 140 to 149
5	Unit #5	IR 150 to 159
6	Unit #6	IR 160 to 169
7	Unit #7	IR 170 to 179
8	Unit #8	IR 180 to 189
9	Unit #9	IR 190 to 199

**Note** 1. The unit number setting switch is factory set to 0.

2. If two or more Special I/O Units are assigned the same unit number, an I/O UNIT OVER error will be generated and the PC will not operate.

3. Make the unit number settings with the power turned off to the PC. If the settings are made with the power on, they will not go into effect until either the power is turned off and then on again or the Special I/O Unit Restart Flag (AR0100 to AR0109) is turned OFF  $\rightarrow$  ON  $\rightarrow$  OFF.

### 3-1-3 Wiring

**Terminal Allocation** 

The following illustration shows the function of each output.

		P0	Voltago output 1 ( )
Voltage output 1 (_)	۵0	ЪU	
	70	B1	Current output 1 (+)
Current output 1 (-)	A1	БО	
Voltago output 2 ( )	<u>۸</u> ۵	DZ	Voltage output 2 (+)
	AZ	B3	Current output 2 (+)
Current output 2 (-)	A3		,
		B4	Voltage output 3 (+)
Voltage output 3 (–)	A4	B5	Current output 3 (+)
Current output 3 (-)	A5		
		B6	Voltage output 4 (+)
Voltage output 4 (-)	A6	B7	Current output 4 (+)
Current output 4 (-)	A7	57	
		B8	Not used.
Not used.	A8	B9	Notwood
			Not usea.

#### **Before Operation**

#### **Output Wiring**

The following diagram shows the external wiring of outputs for the C200H-DA002.



**Note** A single output line cannot be used for voltage and current output at the same time.

#### Output Wiring Considerations

When wiring outputs, apply the following points to avoid noise interference and optimize Analog Output Unit performance.

- Use shielded twisted-pair cable for external connections and power lines.
- Route output cables separately from the AC cable, and do not run the Unit's cables near a main circuit cable, high voltage cable, or a non-PC load cable.
- Be sure to install surge-absorbing diodes or surge absorbers for inductive loads (relays, solenoids, electromagnetic valves, etc.) They should be installed right next to relays and solenoids. Use surge-absorbing diodes with a dielectric strength of at least five times the circuit voltage.



- If there is noise interference from power lines (if, for example, the power supply is shared with electrical welding devices or electrical discharge machines, or if there is a high-frequency generation source nearby) install a noise filter at the power supply output area.
- Use at least a class-3 ground (to 100  $\Omega$  or less), with as heavy a wire as possible (i.e., at least 1.25 mm<sup>2</sup>).

# **3-2** Bit and DM Allocations

#### **IR Allocations**

C200H/C200HS Analog Output Units are allocated ten words each from the portion of the IR area (IR 100 to IR 199) that is reserved for Special I/O Units. The words that are allocated a particular Analog Output Unit depend on the setting of the unit number setting switch on the front panel of the Unit. Those ten words are then reserved as an I/O refresh data area, and the bits that comprise that area are refreshed with every I/O refresh cycle by the PC.



**Note** The unit number that is set for an Analog Output Unit must not be used for any other Special I/O Unit. If overlapping numbers are set, an I/O UNIT OVER error will be generated and operation will be stopped.

#### **IR Allocations**

I/O	Wd	Vd Bit															
	(IR)	15	14	13	12	11	10	09	08	07	06	05	04	03	02	01	00
OUT	n	Sign bit	Outpu	Output 1 setting data													
	n+1	Sign bit	Outpu	Output 2 setting data													
	n+2	Sign bit	Outpu	Output 3 setting data													
	n+3	Sign bit	Outpu	ut 4 se	tting d	ata											

#### **Setting Data**

Output signal range	Setting data (BCD equivalent shown in parentheses)
+4 to +20 mA	0000 to 0FFF (0000 to 4095)
-10 to +10 V	8FFF to 8001, 0000 to 0FFF (-4095 to -0001, 0000 to 4095)

**Note** When the -10 to +10 V range is being used, the 15<sup>th</sup> bit serves as the sign bit. A value of 0 indicates "+" and a value of 1 indicates "-."

### 3-2-1 Programming

Use the MOV(21) instruction to write output data (binary data) from the CPU to the Analog Output Unit.

#### Word Allocation

This program example uses the following settings:

- Unit number: 0 (Words IR 100 to IR 103 are allocated to unit number 0.)
- The following table shows the DM words that contain the output data.

Output number	DM word
Output 1	DM 0000
Output 2	DM 0001
Output 3	DM 0002
Output 4	DM 0003

#### **Program Example**



### 3-3 Troubleshooting

#### **Error Detection**

When an error occurs in an input or in the Unit itself, the error is indicated by an output to a flag in the IR, SR, or AR area. The following tables show the various errors that may occur, along with their probable causes and remedies.

Unit error	Probable causes and operations	Possible remedies
RUN indicator not lit	The RUN indicator on the Unit is not lit even though power is turned on to the PC, and none of the errors described in this table have occurred.	Replace the Unit.

CPU error	Probable causes and operations	Possible remedies	
CPU waiting	The Special I/O Unit is defective.	• Replace the defective Special I/O Unit.	
	<ul> <li>The PC hasn't begun to run.</li> </ul>	• The defective Unit should appear as \$ signs only in the I/O table read operation.	
I/O Unit Over error	<ul> <li>One unit number has been assigned to more than one Special I/O Unit.</li> </ul>	Do not assign the same number to more than one Unit. Use the I/O table read operation to display unit numbers.	
	<ul> <li>SR 25415 will be turned ON and the PC won't oper- ate when an "I/O Unit Over error" occurs.</li> <li>Flags AR 0000 to AR 0011 indicate the duplicated unit number.</li> </ul>		
Special I/O Unit error	<ul> <li>An error has occurred in I/O refreshing between the CPU and the Special I/O Unit.</li> </ul>	Check AR 0000 to AR 0015 for the unit number of the Unit in error. After	
	<ul> <li>SR 25415 will be turned ON but PC operation will continue when a "Special I/O Unit error" occurs.</li> </ul>	correcting the error, restart the Unit by toggling the corresponding restart bit (OFF $\rightarrow$ ON $\rightarrow$ OFF) in AR 0100 to AR 0109. If the error recurs after restarting the Unit, replace the Unit.	

#### Special I/O Unit Error Detection Bit (SR)

Bit	Error	Explanation	Operation status
25415	Duplicated unit number	One number is assigned to more than one Special I/O Unit.	PC operation stops.
	Special I/O Unit error	An error has occurred in the refresh signal between the CPU and the Special I/O Unit	Operation stops only for the faulty Unit.

#### Special I/O Unit Error Flags (AR)

Bit	Item	Function
AR 0000	Unit #0 Error Flag	When one of the CPU errors described above
AR 0001	Unit #1 Error Flag	occurs, the AR bit turns ON for the Unit where the
AR 0002	Unit #2 Error Flag	
AR 0003	Unit #3 Error Flag	
AR 0004	Unit #4 Error Flag	
AR 0005	Unit #5 Error Flag	
AR 0006	Unit #6 Error Flag	
AR 0007	Unit #7 Error Flag	
AR 0008	Unit #8 Error Flag	
AR 0009	Unit #9 Error Flag	

#### Special I/O Unit Restart Bits (AR)

Turn OFF  $\rightarrow$  ON  $\rightarrow$  OFF the Special I/O Unit Restart Bits in the following circumstances:

- After DM data has been set or replaced.
- To restart Unit operation after clearing an error.

The same effect can be achieved by turning  $ON \rightarrow OFF \rightarrow ON$  the power to the PC and then turning it on again.

Bit	Item	Function
AR 0100	Unit #0 Restart Bit	Special I/O Units can be restarted by turning the
AR 0101	Unit #1 Restart Bit	corresponding bits OFF $\rightarrow$ ON $\rightarrow$ OFF.
AR 0102	Unit #2 Restart Bit	
AR 0103	Unit #3 Restart Bit	
AR 0104	Unit #4 Restart Bit	
AR 0105	Unit #5 Restart Bit	
AR 0106	Unit #6 Restart Bit	
AR 0107	Unit #7 Restart Bit	
AR 0108	Unit #8 Restart Bit	
AR 0109	Unit #9 Restart Bit	

# Appendix A Standard Models

# Analog Input Unit

PC	Model
C200H/C200HS	C200H-AD002

# Analog Output Unit

PC	Model	
C200H/C200HS	C200H-DA002	

# Appendix B Specifications

# C200H-AD002 Analog Input Unit

### **General Specifications**

All general specifications of the C200H-AD002 Analog Input Unit conform to those of the C Series.

### **Performance Specifications**

ltem	Specifications			
Number of analog inputs	8 max.			
Input signal range (note 1)	Voltage input	-10 to +10 V	Set for each input number in the allocated DM area.	
		+1 to +5 V		
		0 to 10 V		
	Current input	4 to 20 mA		
Max. input signal (note 2)	Voltage input	±15 V		
	Current input	±30 mA		
Input impedance	Voltage input	1 MΩ min.		
	Current input	250 $\Omega$ (rated v	value)	
Resolution	1/4000 max. (full scale)			
Converted output data (note 3)	Binary data	±10 V range: 87D0 to 07D0 Other ranges: 0000 to 0FA0		
	BCD data	±10 V range: A Other ranges:	A000 to 2000 0000 to 4000	
Accuracy (note 4)	25°C	Voltage input: ±0.25% (full scale) Current input: ±0.40% (full scale)		
	0° to 55°C	Voltage input: Current input:	±0.60% (full scale) ±0.80% (full scale)	
Conversion time (note 5)	2.5 ms max./point			
Isolation	Between input terminals and PC: photocoupler			
	Between input terminals: none			
External connectors	34-pin connector (Honda Communications Industries) Connector for the cable side (One is included with each Unit.)			
	MR-34LFG Set	Connector: MI Cover: MR-34	₹-34FG L	
Power consumption	450 mA max. at 5 VDC			
Dimensions	34.5 x 130 x 109 (W x H x D) mm (see last page of this appendix)			
Weight	290 g			

**Note** 1. When the input range is set to -10 V to +10 V, the most significant bit ( $15^{th}$  bit) becomes the sign bit.

- 2. Operation in ranges beyond the maximum input signals will damage the Unit. Operate within the ranges listed above.
- 3. The accuracy is given for full scale (4000). For example, an accuracy of  $\pm 0.80\%$  means a maximum error of  $\pm 32$  (BCD).
- 4. This is the time it takes for a full range input signal to be converted and to be stored in the memory of the Unit. It takes at least one cycle before the converted data is read by the CPU.

### **Input Specifications**



- **Note** 1. The input signal range (0 to +10 V, +1 to +5 V/+4 to +20 mA, or -10 to +10 V) can be selected for each input number. Refer to *2-3 Functions and Programming* for details on setting the input signal range.
  - If an analog signal is input that exceeds the input signal range (max. value of +10 V or +5 V/20 mA, or min. value of 0 V, +1 V/+4 mA, or -10 V), the digital output will remain fixed at the maximum or minimum value.
  - 3. When the input range is set to -10 V to +10 V, the most significant bit (15<sup>th</sup> bit) becomes the sign bit.
  - When the input range is set to 10 V to +10 V and the analog input signal is 0 V, the digital output will be "0000" and the most significant bit (15<sup>th</sup> bit) will be 0.

# C200H-DA002 Analog Output Unit

All general specifications of the C200H-DA002 Analog Output Unit conform to those of the C Series.

ltem	Specifications			
Number of analog outputs	4			
Output signal range	Voltage outputs	-10 to +10 V		
	Current outputs	4 to 20 mA		
Max. output impedance	Voltage output: 0	.5 Ω		
Max. output current	Voltage output: 1	0 mA		
Max. load resistance	Current output: 3	50 Ω		
Resolution	Voltage outputs 1/8190 max. (full scale)			
	Current outputs	1/4095 max. (full scale)		
Set data	Voltage output: Sign bit +12-bit binary (8FFF to 0FFF) Current output: 12-bit binary (0000 to 0FFF)			
Accuracy	25°C	Voltage outputs: ±0.3% max. (full scale) Current outputs: ±0.5% max. (full scale)		
	0° to 55°C	Voltage outputs: ±0.5% max. (full scale) Current outputs: ±1.0% max. (full scale)		
Conversion time (see Note)	2.5 ms max./point			
Isolation	Between output terminals and PC: photocoupler			
	Between output terminals: none			
External connections	19-pin terminal block (removable)			
Power consumption	600 mA max. at 5 VDC			
Dimensions	34.5 x 130 x 128 (W x H x D) mm (see last page of this appendix)			
Weight	320 g max.			

**Note** This is the time from after the data has been written to the Unit until an analog output appears. The output data will not be correct if output data is rewritten faster than it can be output.

### **Output Specifications**



- **Note** 1. If a digital signal is input that exceeds the output signal range (max. value of +10 V or +20 mA, or min. value of -10 V or +4 mA), the analog output will remain fixed at its maximum or minimum value.
  - 2. When the input range is set to -10 V to +10 V, the most significant bit (15<sup>th</sup> bit) becomes the sign bit.

# **External Dimensions**

Unit: mm

# C200H-AD002 Analog Input Unit



### C200H-DA002 Analog Output Unit



# Installation Dimensions (Unit: mm)

# C200H-AD002 Analog Input Unit



# Appendix C Data Memory Coding Sheet

# C200H-AD002 Analog Input Unit

# **Data Settings**

C200H-	AD002	Unit numb	er:						
lte	m	Input 8	Input 7	Input 6	Input 5	Input 4	Input 3	Input 2	Input 1
Conversion setting	prohibit								
A/D conver	sion data	Bianry or B	CD						
Input signa	l range								
Scaling function	Lower limit								
	Upper limit								
Number of terms for mean value calculation									
Square root function									
Limit	Mode	1 or 2							
warning function	Lower limit								
	Upper limit								

# Data Memory Coding Sheet

C200H-AD002		002	Unit number: DM1_00 to DM1_43		
DM address (rightmost digits)	Data		Usage		
00	0		Bti 09:Limit warning mode (Mode 2 = 1)Conversion prohibit setting (prohibit = 1)Bit 08:Data type setting (BCD = 1)Conversion prohibit setting 		
01			Input signal range (00 specifies –10 to +10 V, 01 specifies 0 to 10 V, and 10 specifies 1 to 5 V/4 to 20 mA.)		
02			Scaling execution Mean value execution		
03			Square root execution Limit warning execution		
04			Input 1 scaling: lower-limit value		
05			Input 1 scaling: upper-limit value		
06			Input 2 scaling: lower-limit value		
07			Input 2 scaling: upper-limit value		
08			Input 3 scaling: lower-limit value		
09			Input 3 scaling: upper-limit value		
10			Input 4 scaling: lower-limit value		
11			Input 4 scaling: upper-limit value		
12			Input 5 scaling: lower-limit value		
13			Input 5 scaling: upper-limit value		
14			Input 6 scaling: lower-limit value		
15			Input 6 scaling: upper-limit value		
16			Input 7 scaling: lower-limit value		
17			Input 7 scaling: upper-limit value		
18			Input 8 scaling: lower-limit value		
19			Input 8 scaling: upper-limit value		
20			Input 1 mean value processing: number of samples		
21			Input 2 mean value processing: number of samples		
22			Input 3 mean value processing: number of samples		
23			Input 4 mean value processing: number of samples		
24			Input 5 mean value processing: number of samples		
25			Input 6 mean value processing: number of samples		
26			Input 7 mean value processing: number of samples		

C20	0H-AD002	Unit number: DM1_00 to DM1_43	
DM address (rightmost digits)	Data	Usage	
27		Input 8 mean value processing: number of samples	
28		Input 1 limit warning: lower-limit value	
29		Input 1 limit warning: upper-limit value	
30		Input 2 limit warning: lower-limit value	
31		Input 2 limit warning: upper-limit value	
32		Input 3 limit warning: lower-limit value	
33		Input 3 limit warning: upper-limit value	
34		Input 4 limit warning: lower-limit value	
35		Input 4 limit warning: upper-limit value	
36		Input 5 limit warning: lower-limit value	
37		Input 5 limit warning: upper-limit value	
38		Input 6 limit warning: lower-limit value	
39		Input 6 limit warning: upper-limit value	
40		Input 7 limit warning: lower-limit value	
41		Input 7 limit warning: upper-limit value	
42		Input 8 limit warning: lower-limit value	
43		Input 8 limit warning: upper-limit value	

# Index

# A–B

A/D conversion data, 14 BCD data, data type setting, 20 binary data, data type setting, 20 block diagram, C200H-DA002, 35 BROKEN WIRE indicator, 27

# С

cable shield, 11 configurations, system, 4 considerations, 5 connector, wiring methods, 11 conversion, prohibiting, 8 conversion data type setting, 20 conversion prohibit settings, 18 conversion prohibition, 8

# D

data memory coding sheet, 52 data type setting, 20 dimensions external, 49 installation, 50 disconnection detection, 27 DM area allocation, C200H-AD002, 13, 15

DM area contents, C200H-AD002, 16

# E—F

error detection C200H-AD002, 31 C200H-DA002, 40

field devices, 3

flags input disconnect, 27 limit warning, 27

indicators C200H-AD002, 8 C200H-DA002, 34

Input Disconnect Flags, 27

input disconnection detection function, 27
input signal range setting, 19
IR area allocation C200H-AD002, 13, 14 C200H-DA002, 39
IR area contents, C200H-AD002, 14

# L

limit warning flags, 27 limit warning function, 25

### Μ

MACHINE No.. *See* unit number mean value function, 24 models, 43

# Ρ

peak value function, 25 precautions, 2, 5 programming examples C200H-AD002, 30 C200H-DA002, 40 protective seal, 11

# S–T

scaling function, 22 Slave Racks, 5 specifications, 45 square root function, 21 switches C200H-AD002, 9 C200H-DA002, 35 troubleshooting C200H-AD002, 31

C200H-DA002, 40

# U–W

unit numbers, setting C200H-AD002, 9 C200H-DA002, 35

Units, number, 5 wiring C200H-AD002, 9 C200H-DA002, 36

### **Revision History**

A manual revision code appears as a suffix to the catalog number on the front cover of the manual.

Cat. No. W229-E1-2

- Revision code

The following table outlines the changes made to the manual during each revision. Page numbers refer to the previous version.

Revision code	Date	Revised content
1	June 1993	Original production
1A	January 1994	<b>Pages ix, 2, 3, 26, 31:</b> Information added to reflect that the C200H-AD002 can also be used with the C200HS.
2	October 1995	Completely revised.