

Ordering information

Example: 55 series plug-in relay, 4 CO (4PDT), 12 V DC coil, lockable test button and mechanical indicator.



Selecting features and options: only combinations in the same row are possible. Preferred selections for best availability are shown in **bold**.

Туре	Coil version	Α	В	С	D
55.32/34	AC-DC	0 - 2 - 5	0	0	0 - 6
	AC	0 - 2 - 5	0	2 - 3 - 4 - 5	0 - 6
	AC	0 - 2 - 5	0	54	/
	DC	0 - 2 - 5	0	2-4-6-7-8-9	0 - 6
	DC	0 - 2 - 5	0	74 - 94	/
55.33	AC-DC	0 - 2 - 5	0	0	0 - 6
	AC	0 - 2 - 5	0	1 - 3 - 5	0 - 6
	DC	0 - 2 - 5	0	1-6-7-8-9	0 - 6
55.12/13/14	AC-DC	0 - 2 - 5	0	0	0 - 1

14

A2

6 = Double LED (DC non-polarized) = Lockable test button + double LED 7 (DC non-polarized) 74 = Lockable test button + double LED

55

- (DC non-polarized) + mechanical indicator
- 8 = LED + diode
- (DC, polarity positive to pin A1/13)
- 9 = Lockable test button + LED + diode (DC, polarity positive to pin A1/13)
- 94 = Lockable test button + LED + diode (DC, polarity positive to pin A1/13) + mechanical indicator

Descriptions: Options and Special versions







13

A1



C: Option 8, 9, 94 LED + diode (DC, polarity positive to pin A1/13)

D: Special versions 6 Rear flange mount

3.6



Lockable test button and mechanical flag indicator (0040)

The dual-purpose Finder test button can be used in two ways:

Case 1) The plastic pip (located directly above the test button) remains intact. In this case, when the test button is pushed, the contacts operate. When the test button is released the contacts return to their former state

Case 2) The plastic pip is broken-off (using an appropriate cutting tool). In this case, (in addition to the above function), when the test button is pushed and rotated, the contacts are latched in the operating state, and remain so until the test button is rotated back to its former position. In both cases ensure that the test button actuation is swift and decisive.



Technical data

Insulation					
Insulation according to EN 61810-1 ed. 2	insulation rated voltage	۷	400 (2-3 pole)	250 (4 pole)	
	rated impulse withstand voltage	kV	3.6 (2-3 pole)	2.5 (4 pole)	
	pollution degree		2		
	overvoltage category		III		
Insulation between coil and contacts (1.2/50 µs)			3.6		
Dielectric strength between open contacts			1,000		
Dielectric strength between adjacent contact			2,000 (2 CO)	2,000 (3 CO)	1,550 (4 CO)
Conducted disturbance immunity					
Burst (550)ns, 5 kHz, on A1 - A2			EN 61000-4-4 level 4 (4 kV)		
Surge (1.2/50 µs) on A1 - A2 (differential mode)			EN 61000-4-5	level 4 (4 kV)	
Other data					
Bounce time: NO/NC			1/4		
Vibration resistance (555)Hz, max. ± 1 mm: NO/NC			15/15		
Shock resistance			16		
Power lost to the environment	without contact current	W	1 (2 pole)	1 (3 pole)	1 (4 pole)
	with rated current	W	3 (2 pole)	4 (3 pole)	3 (4 pole)
Recommended distance between relays mounted on PCB			≥ 5		

Contact specification

F 55 - Electrical life (AC) v contact current

2 and 3 pole relays

55



H 55 - Maximum DC1 breaking capacity



• When switching a resistive load (DC1) having voltage and current values under the curve, an electrical life of $\geq 100 \cdot 10^3$ can be expected.

• In the case of DC13 loads, the connection of a diode in parallel with the load will permit a similar electrical life as for a DC1 load. Note: the release time for the load will be increased.

F 55 - Electrical life (AC) v contact current

