

# PCB Power Relay – G2R

## High-sensitivity Relays

|  |                                 |       |        |         |         |
|--|---------------------------------|-------|--------|---------|---------|
| <b>Rated voltage</b>                         | 5 VDC                           | 6 VDC | 12 VDC | 24 VDC  | 48 VDC  |
| <b>Rated current (50/60Hz) (see Note. 1)</b> | 71.4 mA                         | 60 mA | 30 mA  | 15 mA   | 7.5 mA  |
| <b>Coil resistance (see Note. 1)</b>         | 70 Ω                            | 100 Ω | 400 Ω  | 1,600 Ω | 6,400 Ω |
| <b>Coil inductance (H) (ref. value)</b>      | <b>Armature OFF</b>             | 0.37  | 0.53   | 2.14    | 7.80    |
|  | <b>Armature ON</b>              | 0.75  | 1.07   | 4.27    | 15.60   |
| <b>Must operate voltage</b>                  | 70% max. of rated voltage       |       |        |         |         |
| <b>Must release voltage</b>                  | 15% min. of rated voltage       |       |        |         |         |
| <b>Max. voltage</b>                          | 170% of rated voltage (at 23°C) |       |        |         |         |
| <b>Power consumption</b>                     | Approx. 0.36 W                  |       |        |         |         |

- Note:** 1. The rated current and coil resistance are measured at a coil temperature of 23°C with a tolerance of  $+15\%$ / $-20\%$  (AC rated current) or  $\pm 10\%$  (DC coil resistance)  
 2. Operating characteristics are measured at a coil temperature of 23°C  
 3. Depending on the type of relay, some relays do not have coil specifications. Contact your Omron representative for more details.

## Double-winding Latching Relays

|                           |  |                     |        |         |         |       |
|---------------------------|--|---------------------|--------|---------|---------|-------|
| <b>Rated voltage</b>      | 5 VDC  | 6 VDC               | 12 VDC | 24 VDC  |         |       |
| <b>Set Coil</b>           | <b>Rated current (see note 1.)</b>                   | 167 mA              | 138 mA | 70.6 mA | 34.6 mA |       |
|                           | <b>Coil resistance (see note 1.)</b>                 | 30 Ω                | 43.5 Ω | 170 Ω   | 694 Ω   |       |
|                           | <b>Coil inductance (H) (ref. value)</b>              | <b>Armature OFF</b> | 0.073  | 0.104   | 0.42    | 1.74  |
|                           |  | <b>Armature ON</b>  | 0.146  | 0.208   | 0.83    | 3.43  |
| <b>Reset Coil</b>         | <b>Rated current</b>                                 | 119 mA              | 100 mA | 50 mA   | 25 mA   |       |
|                           | <b>Coil resistance</b>                               | 42 Ω                | 60 Ω   | 240 Ω   | 960 Ω   |       |
|                           | <b>Coil inductance (H) (ref. value)</b>              | <b>Armature OFF</b> | 0.003  | 0.005   | 0.018   | 0.079 |
|                           |  | <b>Armature ON</b>  | 0.006  | 0.009   | 0.036   | 0.148 |
| <b>Must set voltage</b>   | 70% max. of rated voltage                            |                     |        |         |         |       |
| <b>Must reset voltage</b> | 70% max. of rated voltage                            |                     |        |         |         |       |
| <b>Max. voltage</b>       | 140% of rated voltage (at 23°C)                      |                     |        |         |         |       |
| <b>Power consumption</b>  | Set coil: Approx. 850 mW; Reset coil: Approx. 600 mW |                     |        |         |         |       |

- Note:** 1. The rated current and coil resistance are measured at a coil temperature of 23°C with a tolerance of  $\pm 10\%$ .  
 2. Operating characteristics are measured at a coil temperature of 23°C.

## ■ Contact Ratings

PCB/Flux Protection, Plug-in, Quick-connect Terminal Relays

| Item                              | General-purpose, quick-connect terminal |  |   |  | High-capacity                           |  |
|-----------------------------------|---|--|---|--|---|--|
| Number of poles                   | 1 pole                                  |  | 2 poles                                 |  | 1 pole                                  |  |
| Load                              | Resistive load<br>( $\cos\varphi = 1$ ) | Inductive load<br>( $\cos\varphi = 0.4$ ;<br>L/R = 7 ms) | Resistive load<br>( $\cos\varphi = 1$ ) | Inductive load<br>( $\cos\varphi = 0.4$ ;<br>L/R = 7 ms) | Resistive load<br>( $\cos\varphi = 1$ ) | Inductive load<br>( $\cos\varphi = 0.4$ ;<br>L/R = 7 ms) |
| Rated Load                        | 10 A at 250 VAC;<br>10 A at 30 VDC      | 7.5 A at 250 VAC;<br>5 A at 30 VDC                       | 5 A at 250 VAC;<br>5 A at 30 VDC        | 2 A at 250 VAC;<br>3 A at 30 VDC                         | 16 A at 250 VAC;<br>16 A at 30 VDC      | 8 A at 250 VAC;<br>8 A at 30 VDC                         |
| Contact material                  | AgSnIn                                  |  |   |  |   |  |
| Rated carry current               | 10 A                                    |  | 5 A                                     |  | 16 A                                    |  |
| Max. switching voltage            | 380 VAC, 125 VDC                        |  | 380 VAC, 125 VDC                        |  | 380 VAC, 125 VDC                        |  |
| Max. switching current            | 10 A                                    |  | 5 A                                     |  | 16 A                                    |  |
| Max. switching power              | 2,500 VA,<br>300 W                      | 1,875 VA,<br>150 W                                       | 1,250 VA,<br>150 W                      | 500 VA,<br>90 W  | 4,000 VA,<br>480 W                      | 2,000 VA,<br>240 W                                       |
| Failure rate<br>(reference value) | 100 mA at 5 VDC                         |  | 10 mA at 5 VDC                          |  | 100 mA at 5 VDC                         |  |

Note: 1. P level:  $\lambda_{60} = 0.1 \times 10^{-9}$ /operation.

PCB/Flux Protection Relays

| Item                              | Bifurcated contacts                     |  | High-sensitivity                        |  |   |  |
|-----------------------------------|---|--|---|--|---|--|
| Number of poles                   | 1 pole                                  |  | 1 pole                                  |  | 2 poles                                 |  |
| Load                              | Resistive load<br>( $\cos\varphi = 1$ ) | Inductive load<br>( $\cos\varphi = 0.4$ ;<br>L/R = 7 ms) | Resistive load<br>( $\cos\varphi = 1$ ) | Inductive load<br>( $\cos\varphi = 0.4$ ;<br>L/R = 7 ms) | Resistive load<br>( $\cos\varphi = 1$ ) | Inductive load<br>( $\cos\varphi = 0.4$ ;<br>L/R = 7 ms) |
| Rated Load                        | 5 A at 250 VAC;<br>5 A at 30 VDC        | 2 A at 250 VAC;<br>3 A at 30 VDC                         | 5 A at 250 VAC;<br>5 A at 30 VDC        | 2 A at 250 VAC;<br>3 A at 30 VDC                         | 3 A at 250 VAC;<br>3 A at 30 VDC        | 1 A at 250 VAC;<br>1.5 A at 30 VDC                       |
| Rated carry current               | 5 A                                     |  | 5 A                                     |  | 3 A                                     |  |
| Max. switching voltage            | 380 VAC, 125 VDC                        |  | 380 VAC, 125 VDC                        |  | 380 VAC, 125 VDC                        |  |
| Max. switching current            | 5 A                                     |  | 5 A                                     |  | 3 A                                     |  |
| Max. switching power              | 1,250 VA,<br>150 W                      | 500 VA,<br>90 W  | 1,250 VA,<br>150 W                      | 500 VA,<br>90 W  | 750 VA,<br>90 W                         | 250 VA,<br>45 W  |
| Failure rate<br>(reference value) | 1 mA at 5 VDC                           |  | 100 mA at 5 VDC                         |  | 10 mA at 5 VDC                          |  |

Note: P level:  $\lambda_{60} = 0.1 \times 10^{-6}$ /operation.