

# DC/DC converters - QUINT-PS/24DC/24DC/10 - 2320092

Please be informed that the data shown in this PDF Document is generated from our Online Catalog. Please find the complete data in the user's documentation. Our General Terms of Use for Downloads are valid (http://phoenixcontact.com/download)



Primary-switched QUINT DC/DC converter for DIN rail mounting with SFB (Selective Fuse Breaking) Technology, input: 24 V DC, output: 24 V DC/10 A

#### **Product Description**

QUINT DC/DC converter with maximum functionality

DC/DC converters alter the voltage level, regenerate the voltage at the end of long cables or enable the creation of independent supply systems by means of electrical isolation.

QUINT DC/DC converters magnetically and therefore quickly trip circuit breakers with six times the nominal current, for selective and therefore cost-effective system protection. The high level of system availability is additionally ensured, thanks to preventive function monitoring, as it reports critical operating states before errors occur.

#### Why buy this product

- Reliable starting of difficult loads, thanks to the static POWER BOOST power reserve with up to 125% nominal current permanently
- Preventive function monitoring indicates critical operating states before errors occur
- ☑ Constant voltage: output voltage regenerated even at the end of long cables
- ☑ Electrical isolation: for setting up independent supply systems



# **Key Commercial Data**

Packing unit	1 STK
GTIN	4 046356 481885
GTIN	4046356481885
Weight per Piece (excluding packing)	900.000 g
Custom tariff number	85044030
Country of origin	China

#### Technical data

#### **Dimensions**

Width	48 mm
Height	130 mm
Depth	125 mm



# DC/DC converters - QUINT-PS/24DC/24DC/10 - 2320092

## Technical data

## Dimensions

Width with alternative assembly	122 mm
Height with alternative assembly	130 mm
Depth with alternative assembly	51 mm

## Ambient conditions

Degree of protection	IP20
Ambient temperature (operation)	-25 °C 70 °C (> 60 °C Derating: 2,5 %/K)
Ambient temperature (storage/transport)	-40 °C 85 °C
Max. permissible relative humidity (operation)	≤ 95 % (at 25 °C, non-condensing)
Noise immunity	EN 61000-6-2:2005

## Input data

Nominal input voltage range	24 V DC
Input voltage range	18 V DC 32 V DC
Current consumption	14 A (24 V, I <sub>BOOST</sub> )
Inrush surge current	< 15 A (typical)
Power failure bypass	> 12 ms (24 V DC)
Input fuse	25 A (internal (device protection))
Choice of suitable circuit breakers	16 A 20 A (Characteristics B, C, D, K)
Type of protection	Transient surge protection
Protective circuit/component	Varistor

## Output data

Nominal output voltage	24 V DC ±1 %
Setting range of the output voltage (U <sub>Set</sub> )	18 V DC 29.5 V DC (> 24 V DC, constant capacity restricted)
Nominal output current (I <sub>N</sub> )	10 A (-25 °C 60 °C)
POWER BOOST (I <sub>Boost</sub> )	12.5 A (-25°C 40°C permanent, U <sub>OUT</sub> = 24 V DC )
Selective Fuse Breaking (I <sub>SFB</sub> )	60 A (12 ms)
Derating	60 °C 70 °C (2.5%/K)
Connection in parallel	Yes, for redundancy and increased capacity
Connection in series	yes
Max. capacitive load	Unlimited
Active current limitation	Approx. 18 A
Control deviation	< 1 % (change in load, static 10 % 90 %)
	< 2 % (change in load, dynamic 10 % 90 %)
	< 0.1 % (change in input voltage ±10 %)
Residual ripple	< 20 mV <sub>PP</sub>
Peak switching voltages nominal load	< 10 mV <sub>PP</sub> (20 MHz)
Maximum power dissipation in no-load condition	1.6 W
Power loss nominal load max.	24 W

#### General

Net weight	0.9 kg