



**Contents**

<i>Description</i>	<i>Page</i>
5 x 15mm fuses . . . . .	4-2
5 x 20mm IEC fuses . . . . .	4-3
5 x 20mm UL fuses . . . . .	4-5
1/4" x 5/8" to 1" fuses . . . . .	4-6
1/4" x 1 1/4" fast-acting fuses . . . . .	4-7
1/4" x 1 1/4" time-delay fuses . . . . .	4-8
PCB mount fuse holders . . . . .	4-9
PCB fuseclips for 5mm dia. fuses . . . . .	4-11
PCB fuseclips for 1/4" dia. fuses . . . . .	4-12
PCB fuseclips for 9/32", 13/32" and 9/16" dia. fuses . . . . .	4-14

Electronic fuses

5 x 15mm fuses

### C515 (axial leads)

#### C519

##### Specifications

**Description:**  
Time-delay fuse.

**Dimensions:**  
5 x 15mm  
(0.197" X 0.591").

**Construction:**  
Glass tube.

##### Ratings:

- Volts — 125Vac (3.5-7A)
- 250Vac (125mA-3A)
- 32Vdc (self certified)
- Amps — 125mA-7A
- IR — 25A (350mA @ 600Vac)
- 35A (125mA-1A @ 250Vac)
- 100A (1.25-3A @ 250Vac)
- 400A (3.5-7A @ 125Vac)
- 10kA (125mA-3A @ 125Vac)

**Agency information:** CE, UL Listed File E19180, Guide JDYX 125mA-250mA and 375mA-3A, UL Recognized, File E19180, Guide JDYX2, 350mA and 3.5A-7A, CSA Certification File 53787, Class 1422-01, 125mA-250mA and 375mA-3A.

##### Features and benefits

- Time-delay for closer sizing on inductive circuits.

##### Typical application

- Electronic circuits
- Printed circuit boards

##### Catalog numbers (amps)

###### With axial leads

C515-125-R	C515-800-R	C515-2.5-R
C515-250-R	C515-1-R	C515-3-R
C515-350-R	C515-1.25-R	C515-3.5-R
C515-375-R	C515-1.5-R	C515-4-R
C515-500-R	C515-1.6-R	C515-5-R
C515-600-R	C515-2-R	C515-6-R
C515-750-R	C515-2.25-R	C515-7-R

###### Without axial leads

C519-125-R	C519-750-R	C519-2.25-R
C519-250-R	C519-1-R	C519-2.5-R
C519-350-R	C519-1.25-R	C519-3-R
C519-375-R	C519-1.5-R	C519-3.5-R
C519-500-R	C519-1.6-R	C519-4-R
C519-600-R	C519-2-R	C519-5-R

Data Sheet: 2006 (C515) and 2007 (C519)

### C518 (axial leads)

#### C520

##### Specifications

**Description:**  
Fast-acting fuse.

**Dimensions:**  
5 x 15mm  
(0.197" X 0.591").

**Construction:**  
Glass tube.

##### Ratings:

- Volts — 250Vac
- 32Vdc (self certified)
- Amps — 100mA-5A
- IR — 35A (100mA-750mA @ 250Vac)
- 10kA (100mA-5A @ 125Vac)
- 100A (1.5-3.5A @ 250Vac)
- 200A (4-5A @ 250Vac)

**Agency information:** CE, UL Recognized File E19180, Guide JDYX2CSA Certification File 53787, Class 1422-01.

##### Features and benefits

- Small footprint saves space in equipment.
- Fast-acting for maximum component protection.
- Available in ferrule and axial leaded configurations

##### Typical applications

- Electronic circuits
- Printed circuit boards

##### Catalog numbers (amps)

###### With axial leads

C518-100-R	C518-750-R	C518-4-R
C518-125-R	C518-2-R	C518-5-R
C518-250-R	C518-2.5-R	
C518-375-R	C518-3-R	
C518-500-R	C518-3.5-R	

###### Without axial leads

C520-100-R	C520-750-R	C520-3.5-R
C520-125-R	C520-1.5-R	C520-4-R
C520-250-R	C520-2-R	C520-5-R
C520-375-R	C520-2.5-R	
C520-500-R	C520-3-R	

Data Sheet: 2026 (C518) and 2027 (C520)

### C517 (axial leads)

##### Specifications

**Description:** Fast-acting fuse.

**Construction:** Glass tube.

##### Ratings:

- Volts — 350Vac\*
- 32Vdc (self certified)
- Amps — 3A
- IR — 100A @ 350Vac
- 100A @ 250Vac
- 10kA @ 125Vac

\*350Vac/100A IR is UL Recognized

**Agency information:** CE, UL Listing File E19180, Guide JDYX, CSA Certification File 53787, Class 1422-01, UL Recognized, File E19180, Guide JDYX2.

- Small footprint saves space in equipment.
- Fast-acting for maximum component protection.
- 350Vac rating for 277V ballast circuit protection.

##### Typical applications

- Electronic circuits
- Printed circuit boards
- Electronic ballast protection

##### Catalog number (amps)

###### With axial leads

C517-3-R