

EE-SX47/67

NEW

Photomicrosensor with 50- to 100-mA direct switching capacity for built-in application.

- Series includes models that enable switching between dark-ON and light-ON operation.
- Response frequency as high as 1 kHz.
- Easy operation monitoring with bright light indicator.
- Wide operating voltage range: 5 to 24 VDC
- Models in which the light indicator turns ON for dark-ON operation are also available.
- A wide range of variations in eight different shapes.
- Flexible robot cable is provided as a standard feature. *2



CE

Be sure to read *Safety Precautions* on page 8.

*1. Only the EE-SX67 Series has pre-wired models.

*2. Pre-wired models only.

Ordering Information

Connector models

Infrared light

Appearance	Sensing method	Connect-ing method	Sensing distance	Output configuration	Indicator mode	Model	
						NPN output	PNP output
Standard 	Through-beam type (with slot)	Connector (4 poles)	5 mm (slot width)	Dark-ON/Light-ON (selectable) *3	Incident light	EE-SX670	EE-SX670P
					No incident light	EE-SX670A	EE-SX670R
				Light-ON	Incident light	EE-SX470	EE-SX470P
L-shaped 				Dark-ON/Light-ON (selectable) *3	Incident light	EE-SX671	EE-SX671P
					No incident light	EE-SX671A	EE-SX671R
				Light-ON	Incident light	EE-SX471	EE-SX471P
T-shaped 				Dark-ON/Light-ON (selectable) *3	Incident light	EE-SX672	EE-SX672P
					No incident light	EE-SX672A	EE-SX672R
				Light-ON	Incident light	EE-SX472	EE-SX472P
Close-mounting 				Dark-ON/Light-ON (selectable) *3	Incident light	EE-SX673	EE-SX673P
					No incident light	EE-SX673A	EE-SX673R
				Light-ON	Incident light	EE-SX473	EE-SX473P
Close-mounting 				Dark-ON/Light-ON (selectable) *3	Incident light	EE-SX674	EE-SX674P
					No incident light	EE-SX674A	EE-SX674R
				Light-ON	Incident light	EE-SX474	EE-SX474P
T-shaped, slot center: 10 mm 				Dark-ON/Light-ON (selectable) *3	Incident light	EE-SX675 NEW	EE-SX675P NEW
F-shaped 				Dark-ON/Light-ON (selectable) *3	Incident light	EE-SX676 NEW	EE-SX676P NEW
R-shaped 				Dark-ON/Light-ON (selectable) *3	Incident light	EE-SX677 NEW	EE-SX677P NEW

*3. These models can be used as Light-ON when the L terminal and positive (+) terminal are connected to each other. To use them as Dark-ON, do not connect these terminals to each other. When used at light-ON, it is useful to select the connector EE-1001-1. The L terminal and positive (+) terminal of this connector are short-circuited in advance.

Pre-wired Models and Models with Junction Connectors

 Infrared light

Appearance	Sensing method	Sensing distance	Output configuration	Indicator mode	Connecting method	Model	
						NPN output	PNP output
Standard 	Through-beam type (with slot)	 5 mm (slot width)	Dark-ON/ Light-ON (selectable) *	Incident light	Pre-wired models (1 m)	EE-SX670-WR NEW	EE-SX670P-WR NEW
					Models with junction connectors (0.1 m)	EE-SX670-C1 J-R NEW	EE-SX670P-C1 J-R NEW
L-shaped 					Pre-wired models (1 m)	EE-SX671-WR NEW	EE-SX671P-WR NEW
					Models with junction connectors (0.1 m)	EE-SX671-C1 J-R NEW	EE-SX671P-C1 J-R NEW
T-shaped, slot center: 7 mm 					Pre-wired models (1 m)	EE-SX672-WR NEW	EE-SX672P-WR NEW
					Models with junction connectors (0.1 m)	EE-SX672-C1 J-R NEW	EE-SX672P-C1 J-R NEW
Close-mounting 					Pre-wired models (1 m)	EE-SX673-WR NEW	EE-SX673P-WR NEW
					Models with junction connectors (0.1 m)	EE-SX673-C1 J-R NEW	EE-SX673P-C1 J-R NEW
Close-mounting 					Pre-wired models (1 m)	EE-SX674-WR NEW	EE-SX674P-WR NEW
					Models with junction connectors (0.1 m)	EE-SX674-C1 J-R NEW	EE-SX674P-C1 J-R NEW
T-shaped, slot center: 10 mm 					Pre-wired models (1 m)	EE-SX675-WR NEW	EE-SX675P-WR NEW
					Models with junction connectors (0.1 m)	EE-SX675-C1 J-R NEW	EE-SX675P-C1 J-R NEW
F-shaped 					Pre-wired models (1 m)	EE-SX676-WR NEW	EE-SX676P-WR NEW
					Models with junction connectors (0.1 m)	EE-SX676-C1 J-R NEW	EE-SX676P-C1 J-R NEW
R-shaped 					Pre-wired models (1 m)	EE-SX677-WR NEW	EE-SX677P-WR NEW
					Models with junction connectors (0.1 m)	EE-SX677-C1 J-R NEW	EE-SX677P-C1 J-R NEW

* These models can be used as Light-ON when the L line and positive (+) line are connected to each other.
To use them as Dark-ON, do not connect these lines to each other.

Accessories for Models with Connectors (Order Separately)

Type	Cable length	Model	Remarks	
Connector		EE-1001		
		EE-1001-1	L terminal and positive (+) terminal are already short-circuited.	
		EE-1009		
	Connector with Cable	1 m	EE-1006	
			EE-1010	
		2 m	EE-1006	
			EE-1010	
	Connector with Robot Cable	1 m	EE-1010-R	
		2 m	EE-1010-R	
	Connector Hold-down Clip		EE-1006A	For EE-1006 only.

Accessories for Models with Junction Connectors (Order Separately)

Type	Cable length	Model	Remarks
Connector with Robot Cable	2m	EE-1016-R-1 NEW	For EE-SX67□-C1 J-R.