

Flange mount - General purpose relay 10 A

- Faston 187, (4.8 x 0.8 mm)
- 2 & 3 pole changeover contacts
- AC coils & DC coils
- Cadmium Free contacts
- Contacts material options

60.62





- 2 pole, 10 A power contacts
- Flange mount/Faston 187

60.63



- 3 pole, 10 A power contacts
- Flange mount/Faston 187



FOR UL RATINGS SEE:

"General technical information" page V

Contact specification

Contact configuration

2 CO (DPDT)

3 CO (3PDT)

Rated current/Maximum peak current

A

10/20

10/20

Rated voltage/

Maximum switching voltage

V AC

250/400

250/400

Rated load AC1

VA

2500

2500

Rated load AC15 (230 V AC)

VA

500

500

Single phase motor rating (230 V AC)

kW

0.37

0.37

Breaking capacity DC1: 30/110/220 V

A

10/0.4/0.15

10/0.4/0.15

Minimum switching load

mW (V/mA)

500 (10/5)

500 (10/5)

Standard contact material

AgNi

AgNi

Coil specification

Nominal voltage (U_N)

V AC (50/60 Hz)

6 - 12 - 24 - 48 - 60 - 110 - 120 - 230 - 240 - 400

V DC

6 - 12 - 24 - 48 - 60 - 110 - 125 - 220

Rated power AC/DC

VA (50 Hz)/W

2.2/1.3

2.2/1.3

Operating range

AC

(0.8...1.1) U_N

(0.8...1.1) U_N

DC

(0.8...1.1) U_N

(0.8...1.1) U_N

Holding voltage

AC/DC

0.8 U_N / 0.5 U_N

0.8 U_N / 0.5 U_N

Must drop-out voltage

AC/DC

0.2 U_N / 0.1 U_N

0.2 U_N / 0.1 U_N

Technical data

Mechanical life AC/DC

cycles

20 · 10⁶ / 50 · 10⁶

20 · 10⁶ / 50 · 10⁶

Electrical life at rated load AC1

cycles

200 · 10³

200 · 10³

Operate/release time

ms

11/4

11/4

Insulation between coil and contacts (1.2/50 μs)

kV

4

3.6

Dielectric strength

between open contacts

V AC

1000

1000

Ambient temperature range

°C

-40...+70

-40...+70

Environmental protection

RT I

RT I

Approvals (according to type)



Ordering information

Example: 60 series plug-in relay, 3 CO (3PDT), 12 V DC coil, test button and mechanical indicator.

A

6 0 . 1 3 . 9 . 0 1 2 . 0 0 4 0


Series	A: Contact material	D: Special versions
Type	0 = Standard	0 = Standard
1 = 8/11 pin plug-in	5 = AgNi + Au	C: Options
6 = Faston 187 (4.8 x 0.8 mm) with flange mount	B: Contact circuit	0 = None
No. of poles	0 = CO (nPDT)	2 = Mechanical indicator
2 = 2 pole	2 = Bifurcated contacts	3 = LED (AC)
3 = 3 pole	60.12/13 - 6 A only	4 = Lockable test button + mechanical indicator
Coil version		5* = Lockable test button + LED (AC)
4 = Current sensing (60.12/13 only)		54* = Lockable test button + LED (AC) + mechanical indicator
8 = AC (50/60 Hz)		6* = LED + diode (DC, polarity positive to pin 2)
9 = DC		7* = Lockable test button + LED + diode (DC, polarity positive to pin 2)
Coil voltage		74* = Lockable test button + LED + diode (DC, polarity positive to pin 2) + mechanical indicator
See coil specifications		* Options not available for 220 V DC and 400 V AC versions.

Selecting features and options: only combinations in the same row are possible.

Preferred selections for best availability are shown in **bold**.


Type	Coil version	A	B	C	D
60.12/13	AC	0	0	0 - 2 - 3 - 4 - 5	0
	AC	0	0	54	/
	AC	5	0 - 2	0 - 2 - 3 - 4 - 5	0
	AC	5	0 - 2	54	/
	DC	0	0	0 - 2 - 4 - 6 - 7	0
	DC	0	0	74	/
	DC	5	0 - 2	0 - 2 - 4 - 6 - 7	0
	DC	5	0 - 2	74	/
	current sensing	0	0	4	0
60.62/63	AC-DC	0 - 5	0	0	0

Descriptions: Options and Special versions



C: Option 3, 5, 54
LED (AC)

C: Option 6, 7, 74
LED + diode (DC, polarity positive to pin 2)



Lockable test button and mechanical flag indicator (0040, 0050, 0054, 0070, 0074)

The dual-purpose Finder test button can be used in two ways:

Case 1) The plastic pip (located directly above the test button) remains intact. In this case, when the test button is pushed, the contacts operate. When the test button is released the contacts return to their former state.

Case 2) The plastic pip is broken-off (using an appropriate cutting tool). In this case, (in addition to the above function), when the test button is pushed and rotated, the contacts are latched in the operating state, and remain so until the test button is rotated back to its former position.

In both cases ensure that the test button actuation is swift and decisive.

