

Safety relays - PSR-MC42-2NO-1DO-24DC-SC - 2702901

Please be informed that the data shown in this PDF Document is generated from our Online Catalog. Please find the complete data in the user's documentation. Our General Terms of Use for Downloads are valid (<http://phoenixcontact.com/download>)



Safety relay with IO-Link for emergency stop, safety doors, and light grids, up to SILCL 3, Cat. 4, PL e, 2 sensor circuits, automatic or manual, monitored start, 2 enabling current paths, 1 signal output, $U_s = 24\text{ V DC}$, plug-in screw terminal block

Your advantages

- ✓ Up to Cat. 4/PL e according to ISO 13849-1, SILCL 3 according to IEC 62061, SIL 3 according to IEC 61508
- ✓ Single and two-channel control
- ✓ 2 sensor circuits
- ✓ 2 enabling current paths, 1 digital signal output
- ✓ Diagnostic data via IO-Link in combination with PSR-CT safety switches
- ✓ For emergency stop and safety door monitoring, plus evaluation of light grids
- ✓ Manually monitored and automatic activation



Key Commercial Data

Packing unit	1 pc
GTIN	
GTIN	4055626458540
Weight per Piece (excluding packing)	187.900 g
Sales Key	DNA181

Technical data

Note

Utilization restriction	EMC: class A product, see manufacturer's declaration in the download area
-------------------------	---

Dimensions

Width	17.5 mm
Height	112.2 mm
Depth	114.5 mm

Safety relays - PSR-MC42-2NO-1DO-24DC-SC - 2702901

Technical data

Ambient conditions

Ambient temperature (operation)	-25 °C ... 60 °C (observe derating)
Ambient temperature (storage/transport)	-40 °C ... 85 °C
Max. permissible relative humidity (operation)	75 % (on average, 85% infrequently, non-condensing)
Max. permissible humidity (storage/transport)	75 % (on average, 85% infrequently, non-condensing)
Maximum altitude	≤ 2000 m (Above sea level)

Power supply

Designation	A1/A2
Rated control circuit supply voltage U_S	24 V DC -20 % / +25 % (provide external protection)
Rated control supply current I_S	typ. 60 mA
Power consumption at U_S	typ. 1.44 W
Inrush current	typ. 2.5 A ($\Delta t = 500 \mu s$ at U_S)
Filter time	1 ms (at A1 in the event of voltage dips at U_S)
Protective circuit	Serial protection against polarity reversal Suppressor diode

Supply of the IO-Link ports

Designation	L+/L-
Nominal voltage for I/O supply	24 V DC -20 % / +25 % (is provided via the IO-Link interface of the IO-Link master.)
Current consumption	typ. 16 mA
Type of protection	Serial protection against polarity reversal
Protective circuit/component	Suppressor diode

Digital inputs

Input name	Sensor circuit S0
	S12, S22
Description of the input	safety-related sensor inputs
	NPN (S12), NPN/PNP (S22)
Number of inputs	2
Input voltage range "0" signal	0 V DC ... 5 V DC (S12)
	For S22, see note in "Signal generator connection versions" section.
Input voltage range "1" signal	11 V DC ... 30 V DC
Input current range "0" signal	0 mA ... 2 mA (S12, S22)
Inrush current	< 5 mA (typ. with U_S at S12, $\Delta t = 150 ms$)
	< 5 mA (typically with U_S at S22/24 V, $\Delta t = 500 \mu s$)
	> -5 mA (typically with U_S at S22/0 V, $\Delta t = 500 \mu s$)
Current consumption	< 5 mA (Typically with U_S at S12)
	< 5 mA (typically with U_S at S22/24 V)
	> -5 mA (typically with U_S at S22/0 V)
Filter time	1.5 ms (Test pulse width of low test pulses)
	Test pulse rate = 5 x Test pulse width
	Deactivate switch-on pulses/light tests for safety applications.