



**Contents**

<i>Description</i>	<i>Page</i>
5 x 15mm fuses . . . . .	4-2
5 x 20mm IEC fuses . . . . .	4-3
5 x 20mm UL fuses . . . . .	4-5
1/4" x 5/8" to 1" fuses . . . . .	4-6
1/4" x 1 1/4" fast-acting fuses . . . . .	4-7
1/4" x 1 1/4" time-delay fuses . . . . .	4-8
PCB mount fuse holders . . . . .	4-9
PCB fuseclips for 5mm dia. fuses . . . . .	4-11
PCB fuseclips for 1/4" dia. fuses . . . . .	4-12
PCB fuseclips for 9/32", 13/32" and 9/16" dia. fuses . . . . .	4-14

Electronic fuses

5 x 15mm fuses

### C515 (axial leads)

#### C519

**Specifications**

**Description:**  
Time-delay fuse.

**Dimensions:**  
5 x 15mm  
(0.197" X 0.591").

**Construction:**  
Glass tube.

**Ratings:**

- Volts — 125Vac (3.5-7A)
- 250Vac (125mA-3A)
- 32Vdc (self certified)
- Amps — 125mA-7A
- IR — 25A (350mA @ 600Vac)
- 35A (125mA-1A @ 250Vac)
- 100A (1.25-3A @ 250Vac)
- 400A (3.5-7A @ 125Vac)
- 10kA (125mA-3A @ 125Vac)

**Agency information:** CE, UL Listed File E19180, Guide JDYX 125mA-250mA and 375mA-3A, UL Recognized, File E19180, Guide JDYX2, 350mA and 3.5A-7A, CSA Certification File 53787, Class 1422-01, 125mA-250mA and 375mA-3A.

**Features and benefits**

- Time-delay for closer sizing on inductive circuits.

**Typical application**

- Electronic circuits
- Printed circuit boards

**Catalog numbers (amps)**

With axial leads		
C515-125-R	C515-800-R	C515-2.5-R
C515-250-R	C515-1-R	C515-3-R
C515-350-R	C515-1.25-R	C515-3.5-R
C515-375-R	C515-1.5-R	C515-4-R
C515-500-R	C515-1.6-R	C515-5-R
C515-600-R	C515-2-R	C515-6-R
C515-750-R	C515-2.25-R	C515-7-R
Without axial leads		
C519-125-R	C519-750-R	C519-2.25-R
C519-250-R	C519-1-R	C519-2.5-R
C519-350-R	C519-1.25-R	C519-3-R
C519-375-R	C519-1.5-R	C519-3.5-R
C519-500-R	C519-1.6-R	C519-4-R
C519-600-R	C519-2-R	C519-5-R



### C518 (axial leads)

#### C520

**Specifications**

**Description:**  
Fast-acting fuse.

**Dimensions:**  
5 x 15mm  
(0.197" X 0.591").

**Construction:**  
Glass tube.

**Ratings:**

- Volts — 250Vac
- 32Vdc (self certified)
- Amps — 100mA-5A
- IR — 35A (100mA-750mA @ 250Vac)
- 10kA (100mA-5A @ 125Vac)
- 100A (1.5-3.5A @ 250Vac)
- 200A (4-5A @ 250Vac)

**Agency information:** CE, UL Recognized File E19180, Guide JDYX2CSA Certification File 53787, Class 1422-01.

**Features and benefits**

- Small footprint saves space in equipment.
- Fast-acting for maximum component protection.
- Available in ferrule and axial leaded configurations

**Typical applications**

- Electronic circuits
- Printed circuit boards

**Catalog numbers (amps)**

With axial leads		
C518-100-R	C518-750-R	C518-4-R
C518-125-R	C518-2-R	C518-5-R
C518-250-R	C518-2.5-R	
C518-375-R	C518-3-R	
C518-500-R	C518-3.5-R	
Without axial leads		
C520-100-R	C520-750-R	C520-3.5-R
C520-125-R	C520-1.5-R	C520-4-R
C520-250-R	C520-2-R	C520-5-R
C520-375-R	C520-2.5-R	
C520-500-R	C520-3-R	



### C517 (axial leads)

**Specifications**

**Description:** Fast-acting fuse.

**Construction:** Glass tube.

**Ratings:**

- Volts — 350Vac\*
- 32Vdc (self certified)
- Amps — 3A
- IR — 100A @ 350Vac
- 100A @ 250Vac
- 10kA @ 125Vac

\*350Vac/100A IR is UL Recognized

**Agency information:** CE, UL Listing File E19180, Guide JDYX, CSA Certification File 53787, Class 1422-01, UL Recognized, File E19180, Guide JDYX2.

- Small footprint saves space in equipment.
- Fast-acting for maximum component protection.
- 350Vac rating for 277V ballast circuit protection.

**Typical applications**

- Electronic circuits
- Printed circuit boards
- Electronic ballast protection

**Catalog number (amps)**

**With axial leads**  
C517-3-R

