## European Domestic and Industrial Fuse Links

The Bussmann range of European cylindrical fuse links are available in a broad selection of physical sizes and current ratings for applications where the system voltage is 250, 380, 400, 500 & 690 Volts AC.

A range of product is available for domestic applications. These are also available with an optional visual indicator. Fuse links comply with IEC60269-1, 60269-3, 60269-3-1 and also meet the requirements of NF and UNE standards.

Class gL-gG and aM fuse links are intended for industrial applications. All industrial fuse links are available with an operated visible fuse indicator. Sizes 14x51 & 22x58 in both Class gL-gG and aM are also available with a built-in striker for micro-switch operation and remote indication.

All Cooper Bussmann cylindrical fuse links have ceramic bodies and silver-plated copper end caps.

## Domestic & Industrial Modular Fuse Holders

The CH range of modular fuse holders is designed to accommodate European domestic and industrial fuse links. Products meet the requirements of IEC60269 and 60947-3 as well as complying with the requirements of NF & UNE standards.

Most configurations are available in multiple pole configurations and offer IP20 finger-safe protection. An optional LED is available for domestic and industrial modular fuse holders for open circuit indication. Multi-phase connection accessories are also available.

10x38 products (1, 2 & 3 Pole with and without indication) are UL listed and CSA certified. Size 14x51 & 22x58 fuse holders (1, 2 & 3 Pole ONLY) are UL recognised.

14x51 & 22x58 designs are available with a micro-switch attachment for operated fuse indication (when using fuse links with a striker) and with pre-breaking or fuse presence. Please contact Cooper Bussmann for more information.

All Cooper Bussmann domestic and industrial modular fuse holders are manufactured from self-extinguishable polyester material and carry a V0 flammability rating.

Quantity per Pack: 10 pcs

## 6x23

| Rated Current | Part Number Without Indicator | Part Number With Indicator | Voltage (AC) | Breaking Capacity (kA) |
|---|---|---|---|---|
| 2 | CD0623G2 | - | 250V | 6 kA |
| 4 | CD0623G4 | - | | |
| 6 | CD0623G6 | - | | |
| 10 | CD0623G10 | - | | |

## 8x23

| Rated Current | Part Number Without Indicator | Part Number With Indicator | Voltage (AC) | Breaking Capacity (kA) |
|---|---|---|---|---|
| 2 | CD0823G2 | CD0823G2 I | 250V | 6 kA |
| 4 | CD0823G4 | CD0823G4 I | | |
| 6 | CD0823G6 | CD0823G6 I | | |
| 10 | CD0823G10 | CD0823G10 I | | |
| 16 | CD0823G16 | CD0823G16 I | | |

## 10x25



| Rated Current | Part Number Without Indicator | Part Number With Indicator | Voltage (AC) | Breaking Capacity (kA) |
|---|---|---|---|---|
| 6 | CD1025G6 | CD1025G6 I | 250V | 6 kA |
| 10 | CD1025G10 | CD1025G10 I | | |
| 16 | CD1025G16 | CD1025G16 I | | |

## 8x31

| Rated Current | Part Number Without Indicator | Part Number With Indicator | Voltage (AC) | Breaking Capacity (kA) |
|---|---|---|---|---|
| 0.5 | CD0831G0.5 | - | 400V | 20 kA |
| 1 | CD0831G1 | - | | |
| 2 | CD0831G2 | CD0823G2 I | | |
| 4 | CD0831G4 | CD0823G4 I | | |
| 6 | CD0831G6 | CD0823G6 I | | |
| 8 | CD0831G8 | CD0831G8 I | | |
| 10 | CD0831G10 | CD0823G10 I | | |
| 12 | CD0831G12 | CD0831G12 I | | |
| 16 | CD0831G16 | CD0823G16 I | | |
| 20 | CD0831G20 | CD0831G20 I | | |
| 25 | CD0831G25 | CD0831G25 I | | |

## 10x31



| Rated Current | Part Number Without Indicator | Part Number With Indicator | Voltage (AC) | Breaking Capacity (kA) |
|---|---|---|---|---|
| 16 | CD1031G16 | CD1031G16 I | 400V | 20 kA |
| 20 | CD1031G20 | CD1031G20 I | | |
| 125 | CD1031G25 | CD1031G25 I | | |

## 10x38



| Rated Current | Part Number Without Indicator | Part Number With Indicator | Voltage (AC) | Breaking Capacity (kA) |
|---|---|---|---|---|
| 25 | CD1038G25 | CD1038G25 I | 400V | 20 kA |
| 32 | CD1038G32 | CD1038G32 I | | |

## 8x36

| Rated Current | Part Number Without Indicator | Part Number With Indicator | Voltage (AC) | Breaking Capacity (kA) |
|---|---|---|---|---|
| 2 | CD0836G2 | CD0836G2 I | 400V | 20 kA |
| 4 | CD0836G4 | CD0836G4 I | | |
| 6 | CD0836G6 | CD0836G6 I | | |
| 10 | CD0836G10 | CD0836G10 I | | |
| 16 | CD0836G16 | CD0836G16 I | | |
| 20 | CD0836G20 | CD0836G20 I | | |
| 25 | CD0836G25 | CD0836G25 I | | |
| 32 | CD0836G32 | CD0836G32 I | | |