

Safety switch sensor - PSR-CT-C-SEN-1-8 - 2702972

Please be informed that the data shown in this PDF Document is generated from our Online Catalog. Please find the complete data in the user's documentation. Our General Terms of Use for Downloads are valid (<http://phoenixcontact.com/download>)



Proximity safety circuit up to Cat. 4, PL e (EN ISO 13849), SIL 3 (IEC 61508), unicode sensor with RFID coding, model 4 (EN ISO 14119), automatic or manual start, integrated diagnostics, 24 V DC supply, IP69K, M12 connector

Product Description

The PSR-CT safety circuit consists of a combination of a PSR-CT-...-SEN-1-8 sensor with varying coding types and a coded PSR-CT-C-ACT actuator. It provides maximum tamper protection and the highest level of safety in accordance with EN ISO 14119. The PSR-CT safety circuit is available with the following types of coding:

Fixcode: For the sensor to detect the actuator, the actuator must first be associated with the sensor via a learning process. The learning process can only be completed once. The sensor and actuator are then permanently assigned to each other by their coding. Safety circuits with fixcode evaluation achieve a high coding level.

Unicode: For the sensor to detect the actuator, the actuator must first be assigned to the sensor via a learning process. The learning process for a new actuator can be repeated any number of times. The sensor only detects the last learned actuator. Safety circuits with unicode evaluation achieve a high coding level.


Multicode: The sensor detects every actuator of the approved type. No specific actuator code can be assigned. Safety circuits with multicode evaluation achieve a low coding level.

Your advantages

- ✓ Integrated reset function on the switch
- ✓ 4 actuation settings, 3 travel directions
- ✓ Tamper protection via RFID transponder technology
- ✓ Rapid diagnostics, thanks to comprehensive status information
- ✓ Consistent M12 connection technology for convenient installation
- ✓ Safe series connection in accordance with EN ISO 14119
- ✓ Flexible use, thanks to compact design
- ✓ Safe, cost-effective complete solution



Key Commercial Data

| | |
|--------------------------------------|---|
| Packing unit | 1 pc |
| GTIN |  4 055626 446899 |
| GTIN | 4055626446899 |
| Weight per Piece (excluding packing) | 40.800 g |
| Custom tariff number | 85365019 |

Safety switch sensor - PSR-CT-C-SEN-1-8 - 2702972

| | |
|-------------------|---------|
| Country of origin | Germany |
|-------------------|---------|

Technical data

Dimensions

| | |
|--------|---------|
| Width | 26.5 mm |
| Height | 40 mm |
| Depth | 18 mm |

Ambient conditions

| | |
|---|------------------|
| Ambient temperature (operation) | -25 °C ... 55 °C |
| Ambient temperature (storage/transport) | -40 °C ... 70 °C |

Power supply

| | |
|---------------------|--|
| Supply voltage | 24 V DC $\pm 15\%$ (PELV, controlled, residual ripple < 5%) |
| Current consumption | max. 40 mA |
| Protection | min. 0.25 A (to be performed externally) |
| | max. 8 A (to be performed externally) |

Safety outputs

| | |
|---|--|
| Designation | FO1A, FO1B |
| Output description | Semiconductor outputs, p-wired |
| Number of outputs | 2 |
| Output voltage | min. ($U_B - 1.5\text{ V}$ (HIGH FO1A, FO1B)) |
| | max. (U_B (HIGH FO1A, FO1B)) |
| | min. 0 V DC (LOW FO1A/FO1B) |
| | max. 1 V DC (LOW FO1A/FO1B) |
| Switching current | min. 1 mA (per safety output) |
| | max. 150 mA (per safety output) |
| Short-circuit-proof | yes |
| Utilization category in accordance with IEC 60947-5-2 | 150 mA (24 V (DC13)) |
| Note on protection circuit | NOTE: Protect the outputs under inductive loads with a freewheeling diode. |
| Residual current | $\leq 0.25\text{ mA}$ |

Alarm outputs

| | |
|---------------------|-------------------------------------|
| Designation | DGN |
| Output description | p-wired |
| Number of outputs | 1 |
| Short-circuit-proof | yes |
| Output voltage | min. ($U_B - 1.5\text{ V}$ (HIGH)) |
| | max. (U_B (HIGH)) |
| | min. 0 V DC (LOW) |
| | max. 1 V DC (LOW) |
| Current I_{DGN} | min. 1 mA |

Times