

Octal Free Screw Terminal Socket



Description:


This range of compact sockets manufactured Nylon PA6 and can be DIN-rail, panel or chassis mounted products The sockets are suitable for use with Tempatron 8 and 11 pin timers and process controllers. All screw terminals are shrouded and finger proofed to maximise safety. Terminals are rated at 5A and 10A at 250V AC depending on type.

Features:

- 10A contact rating
- Screw terminals

Specifications:

Contact Rating	: 10A at 250V AC
Insulation	: >1,000MΩ
Dielectric Strength	: 2kV _{RMS} 50Hz for 1 minute
Fixings	: M3 screws or 35mm DIN rail (DIN-EN 50022)
Material	: Nylon PA6
Weight	: 30g



Dimensions : Millimetres

Part Number Table

Description	Part Number
Octal Free Screw Terminal Socket	MCS8F

Important Notice : This data sheet and its contents (the "Information") belong to the members of the Premier Farnell group of companies (the "Group") or are licensed to it. No licence is granted for the use of it other than for information purposes in connection with the products to which it relates. No licence of any intellectual property rights is granted. The Information is subject to change without notice and replaces all data sheets previously supplied. The Information supplied is believed to be accurate but the Group assumes no responsibility for its accuracy or completeness, any error in or omission from it or for any use made of it. Users of this data sheet should check for themselves the Information and the suitability of the products for their purpose and not make any assumptions based on information included or omitted. Liability for loss or damage resulting from any reliance on the Information or use of it (including liability resulting from negligence or where the Group was aware of the possibility of such loss or damage arising) is excluded. This will not operate to limit or restrict the Group's liability for death or personal injury resulting from its negligence. Multicomp is the registered trademark of the Group. © Premier Farnell plc 2012.

www.element14.com
www.farnell.com
www.newark.com

