

# DATASHEET

**SIEMENS**

3TF2001-6BB4

**OTHER SYMBOLS:**

3TF20016BB4, 3TF2001 6BB4, 3TF2001-6BB4

**RGB ELEKTRONIKA AGACIAK CIACIEK  
SPÓŁKA JAWNA**

Jana Długosza 2-6 Street  
51-162 Wrocław  
Poland

✉ [biuro@rgbelektronika.pl](mailto:biuro@rgbelektronika.pl)

☎ +48 71 325 15 05



[www.rgbelektronika.pl](http://www.rgbelektronika.pl)



[www.rgbautomatyka.pl](http://www.rgbautomatyka.pl)

# YOUR PARTNER IN MAINTENANCE

Repair **this product** with RGB ELEKTRONIKA

[ORDER A DIAGNOSIS »](#)



At our premises in Wrocław, we have a fully equipped servicing facility. Here we perform all the repair works and test each later sold unit. Our trained employees, equipped with a wide variety of tools and having several testing stands at their disposal, are a guarantee of the highest quality service.

Buy **this product** at RGB AUTOMATYKA

[BUY »](#)

# SIEMENS

## Product data sheet

**3TF2001-6BB4**


CONTACTOR, SIZE 00, 3-POLE AC-3,  
4KW/400V, SOLDER-PIN CONN. SCREW MOUNTING  
(DIAGONAL) AUXILIARY CONTACT 01E (1NC) DC  
SOLENOID SYSTEM DC 24V

### General details:

Number of poles	3
Size of the contactor	00

### Control circuit:

Design of activation of the operating mechanism	conventional
Type of voltage	DC
Control supply voltage	
• for DC / rated value / minimum	24 V
• for DC / rated value / maximum	24 V

### Main circuit:

Number of NO contacts / for main contacts	3
Number of NC contacts / for main contacts	0
Operating current	
• at AC-3 / at 400 V / rated value	9 A
• at AC-1 / at 400 V / rated value	16 A
Service power	
• at AC-3 / at 400 V / rated value	4 kW
• at AC-1 / at 400 V / rated value	10 kW

### Auxiliary circuit:

Identification number and letter for switching elements	01 E
Number of NO contacts / for auxiliary contact	0
Number of NC contacts / for auxiliary contact	1
Connection type:	
Design of the electrical connection / for main current circuit	solder pin connectors
Design of the electrical connection / for auxiliary and control current circuit	solder pin connectors
Mechanical design:	
Type of fixing/fixation	screw fixing
Type of fixing/fixation / Series installation	Yes

**last change:** 10/31/2006

<b>Technical Assistance:</b>	Telephone:	+49 (0) 911-895-5900 (8°° - 17°° CET)
	Fax:	+49 (0) 911-895-5907
	E-Mail:	technical-assistance@siemens.com
	Internet:	www.siemens.de/lowvoltage/technical-assistance